



Quality Products. Service Excellence.

Peter W Dahl Transformers PWAHL Series

Magnetics for Amateur Radio Products



This listing of transformers and chokes is directly from the Peter W. Dahl files. They are arranged in alpha-numeric order beginning with AAA and ending with 999.

These transformers are usually built to order one at a time. Units we have already built are shown with Hammond part numbers. If you do not see a part number listed - remember that many of these designs are now decades old - a few may have been originally designed using "unobtainium". It is always best to confirm availability by phone or e-mail.



Some Hipersil C-Core models (Style #8, #9 & #10) need to be quoted by our office (due to constant changes & high minimum charges imposed by current C-Core suppliers). We are constantly updating pricing as we quote and/or build units. Most "E-I" lamination units are normally shipped in our 6 week lead time.

Stock units can usually be shipped next business day!



Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
ADVANCED RADIO DEVICES 230A PLATE TRANSFORMER (2 EA 3CX800A7'S)		A-274 C-Core	10	240VCT, 60Hz	1750 VRMS @ 1.1AMP CCS	37
ADVANCED RADIO DEVICES 230AX 50/60 HZ VERSION OF ARD 230A WITH TAPS		A-0480/ C-CORE	10	200-220-234 VCT 50/60 HZ	1750 VRMS @ 1.1 AMP CCS	46
ADVANCED RADIO DEVICES 230C PLATE XFMR FOR 3 TUBE COMMERCIAL VERSION		A-0518/ C-CORE	10	200-220-234 VCT 50/60 HZ	1750 VRMS @ 2.4 AMP CCS	66
ADVANCED RADIO DEVICES 230M 60 HZ VERSION OF 230AX WITH 1.4A RATING		A-0480/ C-CORE	10	200-220-234 VCT 60 HZ 1PH	750 VRMS @ 1.4 AMP CCS	46
ALPHA A70V POWER TRANSFORMER FOR ALPHA VAPOR COOLED 3CV1500A7 LINEAR		A-0393/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 0-2000-3000 VAC @ 0.3A CCS S2) 5.0 VCT @ 30A CCS S3) 0-22-44-66 VAC @ 1A CCS	23
ALPHA 76A POWER TRANSFORMER FOR ALPHA MODELS 76A, 76PA, 76CA & 78	PWDP13139	B-0393/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 0-1200-1950 VAC @ 0.5A CCS S2) 40 VCT @ 0.5A CCS S3) 25 VAC @ 1A CCS S4) 6.3 VAC @ 9.6A CCS	23
ALPHA 76A-1 POWER XFMR FILAMENT WINDING FOR 3CX800A7'S		A-0393/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 0-1100-1750 VAC @ 0.5A CCS S2) 40 VCT @ 0.5A CCS S3) 25 VAC @ 1A CCS S4) 13.5 VAC @ 3.0A CCS	23

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
ALPHA 76A-2 POWER XFMR SPECIAL HEAVY DUTY 3CX800A7'S VERSION	PWDP13047	B-0393/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 0-1200-1950 VAC @ 0.5A CCS S2) 40 VCT @ 0.5A CCS S3) 25 VAC @ 1A CCS S4) 13.5 VAC @ 3.0A CCS	23
ALPHA 76PA 50 HZ SPECIAL PWR 115/230 VAC 50 HZ PRI & 20 VAC BUCK WIND		A-0393/ C-CORE	10	0-115 & 0-115 VAC 50 HZ 1 PH	S1) 0-1100-1750 VAC @ 0.5A CCS S2) 40 VCT @ 0.5A CCS S3) 20 VAC @ 1A CCS S4) 6.3 VAC @ 9.6A CCS	23
ALPHA A77 POWER XFMR FOR ORIGINAL ETO PA-77 LINEAR AMPLIFIER	PWDP13069	A-0393/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 0-1800-2800 VAC @ 0.7A ICAS S2) 0-22-66 VAC @ 0.5A CCS S3) 5.0 VAC @ 10A CCS	23
ALPHA A77S POWER TRANSFORMER INBOARD TRANSFORMER FOR 2 TUBE ALPHA 77	PWDP13107	A-0525/ C-CORE	9	120/240 VAC 60 HZ 1PH	S1) 0-1800-2800 VAC @ 1.2A CCS S2) 5 VAC @ 20A CCS S3) 50 VAC @ 1.0A CCS S4) 0-22-44 VAC @ 500MA CCS	49
ALPHA A77S POWER TRANSFORMER INBOARD TRANSFORMER FOR 2 TUBE ALPHA 77	PWDP13116	A-0525/ C-CORE	9	220 VAC 50/60 HZ 1PH	S1) 0-1800-2800 VAC @ 1.2A CCS S2) 5 VAC @ 20A CCS S3) 50 VAC @ 1.0A CCS S4) 0-22-44 VAC @ 500MA CCS	49
ALPHA A77S-X OUTBOARD PLATE ADVERTISED UNIT, 6 KVA OUTBOARD PLATE		A-0525/ C-CORE	10	230 VAC 60 HZ 1 PH	0-1800-3000 VAC @ 2.0 AMP CCS	86
ALPHA A77S-X0 OUTBOARD PLATE 6 KVA OUTBOARD PLATE WITH TAPPED PRIMARY		A-0525/ C-CORE	10	0-210-220-230 VAC 60 HZ 1 PH		86
ALPHA A77S-X1 OUTBOARD PLATE MODIFIED VERSION OF A77S-X OUTBOARD PLT		A-0525/ C-CORE	10	0-230-240-250 VAC 60 HZ 1 PH	0-1800-2800 VAC @ 2.0 AMP CCS	86
ALPHA A77S-1 POWER TRANS SPECIAL HIGHER VOLTAGE MODEL		A-0525/ C-CORE	10	120/240 VAC 60 HZ 1PH	S1) 0-1800-3200 VAC @ 1.05A CCS S2) 5 VAC @ 20A CCS S3) 50 VAC @ 1.0A CCS S4) 0-22-44 VAC @ 500MA CCS	49
ALPHA A77S-1-J POWER TRANS HV MODEL WITH 100/200 VAC 60 HZ JAP PRI		A-0525/ C-CORE	9	100/200 VAC 60 HZ 1PH	S1) 0-1800-3200 VAC @ 1.05A CCS S2) 5 VAC @ 20A CCS S3) 30 VAC @ 1.0A CCS S4) 0-22-44 VAC @ 500MA CCS	49
ALPHA A77S-3 POWER TRANS SPECIAL WITH 3000 VAC SEC HI-TAP		A-0525/ C-CORE	9	120/240 VAC 60 HZ 1PH	S1) 0-1800-3000 VAC @ 1.05A CCS S2) 5 VAC @ 20A CCS S3) 50 VAC @ 1.0A CCS S4) 0-22-44 VAC @ 500MA CCS	49
ALPHA A77S-4 POWER TRANS SPECIAL 3400/2400 SEC VAC MODEL (NOTE: Installation requires modification to the power supply components)	PWDP13009	A-0525/ C-CORE	9	120/240 VAC 50/60 HZ 1PH	S1) 0-2400-3400 VAC @ 0.9A CCS S2) 5 VAC @ 20A CCS S3) 50 VAC @ 1.0A CCS S4) 0-22-44 VAC @ 500MA CCS	49

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
ALPHA 78 50 HZ JAPAN SPECIAL FOR ALPHA 78 WITH 100/200V 50 HZ		A-0393/ C-CORE	10	0-100 & 0-100 VAC 50 HZ 1 PH		S1) 0-1100-1750 VAC @ 0.5A CCS S2) 40 VCT @ 0.5A CCS S3) 5 VAC @ 1A CCS (FAN BUCKING WINDING) S4) 6.3 VAC @ 9.6A CCS	23	
ALPHA 78 50 HZ SPECIAL POWER SPECIAL FOR ALPHA 78 WITH 208/240V 50 HZ		A-0393/ C-CORE	10	0-120 & 0-88-120 VAC 50 HZ 1 PH		S1) 0-1100-1750 VAC @ 0.5A CCS S2) 40 VCT @ 0.5A CCS S3) 25 VAC @ 1A CCS S4) 6.3 VAC @ 9.6A CCS	23	
ALPHA 86 SPECIAL TRANSFORMER NON-STD DIMS/MTG, WIRES ONLY, NO MOLEX		EI-225RX 4" 29GAM6X	4	120/240 VAC 60 HZ 1 PH		S1) 0-1240-1760 VAC @ 0.7A CCS S2) 48 VCT @ 1A CCS (28 VDC @ 3A) S3) 14 VCT @ 2A CCS (5 43 VDC @ 3A) S4) 13.5 VAC @ 3A CCS (FILS) S5) 25 VAC @ 1A CCS	43	
ALPHA 87 POWER TRANSFORMER - REV K (NOT THE SAME AS THE ALPHA 87a) ALPHA POWER P/N TPX-X133	PWDP13140	A-0516/ C-CORE	9	0-200-220-240 VAC 50/60 HZ 1 PH		S1) 0-1280-1900 VAC @ 1.5A CCS S2) 7.8 VAC @ 4A CCS S3) 14.45 VAC @ 3A CCS S4) 52 VCT @ 3.5A CCS	33	
ALPHA POWER P/N TPX-X168 ALPHA 91b AND 99 POWER TRANSFORMER	PWDP13049	A-0516/ C-CORE	9	0-100-120 & 0-100-120 VAC 50/60 HZ 1 PH		S1) 0-2050 VAC @ 1.5A CCS S2) 105 VAC @ 0.5A CCS S3) 310 VAC @ 0.5A CCS S4) 28 VCT @ 3.0A CCS S5) 13.3 VAC @ 7.2A CCS	37	
AMERITRON AL-80A HD POWER SPECIAL HV MODEL FOR FWB&CAP (4000 VDC)		EI-175 X 4" 29G M6X	4	240 VAC 60 HZ 1 PH		S1) 2900 VAC @ 600 MA ICAS S2) 13.8 VAC @ 5A ICAS S3) 5.0 VCT @ 15A CCS	25	
MODIFIED AMERITRON AL-80A HD POWER SPECIAL HV MODEL FOR FWB&CAP (4000 VDC) NO 5V OR 13.8V WINDINGS	PWDP13242	EI-175 X 4" 29G M6X	4	240 VAC 60 HZ 1 PH		S1) 2900 VAC @ 600 MA ICAS	24	
AMERITRON AL-80A NV POWER NORMAL PLATE VOLTS, HIGHER CURRENT MODEL		EI-175 X 4" 29GM6X	4	120/240 VAC 60 HZ 1 PH		S1) 2100 VAC @ 450 MA ICAS S2) 13.8 VAC @ 5A ICAS S3) 5.0 VCT @ 15A CCS	25	
AMERITRON P/N AR418-SP AL-1200 PLATE TRANSFORMER WITH 208V TAP		A-0274/ C-CORE	10	0-120 & 0-88-120 VAC 60 HZ 1PH		2570 VAC @ 800 MA ICAS	37	
AMERITRON P/N AR418-1D AL-1200 / AL-1500 / AL-82 PLATE TRANSFORMER	PWDP13010	A-0274/ C-CORE	10	0-120 & 0-100-120 VAC 60 HZ 1PH		2570 VAC @ 800 MA ICAS	37	
AMP SUPPLY #LK-450 HV POWER HIGH VOLTAGE POWER TRANSFORMER		A-0393/ C-CORE	10	110/220 VAC 50 HZ 1 PH		2200 VAC @ 400 MA CCS	23	
AMP SUPPLY #LK-450 LV POWER LOW VOLTAGE POWER TRANSFORMER		EI-150 X 1.5	4	110/220 VAC 50 HZ 1 PH		S1) 5.5 VCT @ 15A CCS S2) 0-10-20 VAC @ 2A CCS	8	
AMP SUPPLY #LK-450 POWER PLATE & FIL XFMR FOR SINGLE 3-500Z	PWDP13134	EI-175 X 2.5" 29GAM6	4	120/240 VAC 60 HZ 1 PH		S1) 2080 VAC @ 0.4A ICAS S2) 5.5 VCT @ 15A CCS S3) 11 VAC @ 2A CCS	17	

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
AMP SUPPLY #LK-500B		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 2135 VAC @ 500MA CCS	S2) 12 VAC @ 1.5A CCS	23	
AMP SUPPLY #LK-500C		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 2135 VAC @ 500MA CCS		23	
AMP SUPPLY #LK-500C-200 JAPANESE PRIMARY		A-393 C-CORE	10	100/200 VAC 60 HZ 1PH	S1) 2135 VAC @ 500MA CCS		23	
AMP SUPPLY #LK-500F-1 FILAMENT TRANSFORMER FOR LK-500 AMP	PWDF13229	EI-150 X 1.5	4	115/230 VAC 60 HZ 1PH	0S1) 5.5 VCT @ 30A CCS		8	
AMP SUPPLY #LK-500F-2 FIL & CONTROL FOR 2 EA 3-500Z TUBES	PWDP13232	EI-150 X 1.5	4	115/230 VAC 60 Hz 1PH	S1) 5.5 VCT @ 30A S2) 0-10-18 VAC @ 2A		8	
AMP SUPPLY #LK-500F-3 FIL & CONTROL FOR 3 EA 3-500Z TUBES		EI-175 X 2	4	115/230 VAC 60 HZ 1PH	S1) 5.5 VCT @ 50A S2) 0-10-18 VAC @ 2A		14	
AMP SUPPLY #LK-500F2-200 JAPANESE PRIMARY		EI-150 X 1.5	4	100/200 VAC 60 HZ 1PH	S1) 5.5 VCT @ 30A CCS S2) 0-10-18 VAC @ 2A CCS		8	
AMP SUPPLY #LK-500ZA-1 SPECIAL FOR OMEGA ELECTRONICS - LV MODEL		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 2000 VAC @ 500MA CCS		23	
AMP SUPPLY #LK-800EXT		A-480 C-CORE	10	234 VAC 60 Hz	S1) 1800 VAC @ 1.5A CCS		46	
AMP SUPPLY #LK-800EXT H/L HD HIGHER VOLTAGE HIGHER CURRENT MODEL	PWDP13128	A-0518/ C-CORE	10	234 VAC 60 HZ 1 PH	S1) 0-1800-2500 VAC @ 1.5A CCS		66	
AMP SUPPLY #LK-800EXT HI-LO EXTERNAL TRANSFORMER FOR LK-800 LINEAR		A-0480/ C-CORE	10	234 VAC 60 HZ 1 PH	S1) 0-1800-2135 VAC @ 1.3A CCS		46	
AMP SUPPLY #LK-800EXT-SP SPECIAL HIGHER VOLTAGE MODEL		A-0480/ C-CORE	10	234 VAC 60 HZ 1 PH	S1) 0-2050-2450 VAC @ 1.1A CCS		46	
AMP SUPPLY #LK-800EXT-SPL HIGHER VOLTAGE 50 HZ VERSION		A-0480/ C-CORE	10	220 VAC 50 HZ 1 PH	S1) 2050 VAC @ 1.5A ICAS		46	
AMP SUPPLY #LK-800EXT100/200 JAPANESE PRIMARY VOLTAGES		A-0480/ C-CORE	10	100/200 VAC 60 Hz	S1) 1800 VAC @ 1.5A CCS		46	
AMP SUPPLY #LK-800F FILAMENT TRANSFORMER FOR LK-800 LINEAR		EI-150 SQ	4	117/234 VAC 60 Hz 1PH	S1) 13.6 VAC @ 9A S2) 12 VAC @ 2A		8	
AMP SUPPLY #LK-800F-1	PWDP13080	EI-150 X 1.5	4	117/234 VAC 60 Hz 1PH	S1) 13.6 VAC @ 9A S2) 0-10-18 VAC @ 2A		8	
AMP SUPPLY #LK-800F-1 (with C.T on 13.6 VAC winding)	PWDP13093	EI-150 X 1.5	4	117/234 VAC 60 Hz 1PH	S1) 13.6 VAC @ 9A - with C.T. S2) 0-10-18 VAC @ 2A		8	
AMP SUPPLY #LK-800F-100/200 JAPANESE PRIMARY VOLTAGES		EI-150 SQ	4	100/200 VAC 60 Hz 1PH	S1) 13.6 VAC @ 9A S2) 12 VAC @ 2A		8	
AMP SUPPLY #LK-800F/208 LK-800F WITH 208 VAC PRIMARY		EI-150 SQ	4	208 VAC 60 Hz 1PH	S1) 13.6 VAC @ 9A S2) 12 VAC @ 2A		8	
AMP SUPPLY #LK-800P		A-0393/CA-393/MA	10	117/234 VAC 60 Hz 1PH	S1) 1800 VAC @ 500 MA CCS		23	
AMP SUPPLY #LK-800P-100/200 JAPANESE PRIMARY VOLTAGES		A-0393 / C-CORE	10	100/200 VAC 60 Hz 1PH	S1) 1800 VAC @ 500 MA		23	
AMP SUPPLY P/N AL27-1.2 G		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 2700 VAC @ 1.2A CCS		46	
AMP SUPPLY P/N AL27-1.2 N		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1PH	S1) 2700 VAC @ 1.2A CCS		46	
AMP SUPPLY P/N AL88T-1 IMPROVED VERSION OF AL88T		B-0393/ C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-1800-2400 VAC @ 1.0A CCS* S2) 26 VAC @ 2A CCS S3) 5.0 VAC @ 10A CCS		23	
ARCOS P/N IVS-2000 POWER XFMR FOR J. FRED MERRY VHF AMP		A-203 C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 840 VAC @ 1.5A CCS S2) 140 VAC @ 0.2A CCS S3) 7.8 VAC @ 6A CCS		30	

Description	Hammond Part Number	Core	Style (see above)	Approx. Weight (lbs)		
				Primary	Secondary	
ARCOS P/N IVS-2700 POWER TRANSFORMER		A-480 C-CORE	10	230 VAC 60 HZ 1 PH	S1) 0-1650-1790-1935 VAC @ 1.5A ICAS S2) 13.5 VAC @ 3A CCS	46
ARRL-001 PLATE TRANSFORMER		A-480 C-CORE	10	0-220-240 VAC 60 HZ 1PH	S1) 2650 VAC @ 1.5A ICAS	46
ARRL-001-01 PLATE TRANSFORMER WITH 110 VAC PRIMARY		A-480 C-CORE	10	110 VAC 60 HZ 1PH	S1) 0-2000-2300-2650 VAC @ 1.5A ICAS	46
ARRL-002 PLATE TRANSFORMER	PWDP13253	A-480 C-CORE	10	0-220-240 VAC 60 HZ 1PH	0-1770-2125-2500 VAC @ 1.5A ICAS	46
ARRL-002-1 PLATE TRANSFORMER		A-0480/ C-CORE	10	110/220 VAC 60 HZ 1PH	S1) 0-1500-2000-2500 VAC @ 1.5A ICAS	46
ARRL-002-2 PLATE TRANSFORMER	PWDP13029	A-0480/ C-CORE	10	110/220 VAC 60 HZ 1PH	S1) 0-1500-2000-2500- 2750 VAC @ 1.5A ICAS	46
ARRL-002-2 (MODIFIED) PLATE TRANSFORMER	PWDP13146	A-0480/ C-CORE	10	110/220/230/240 VAC 60 HZ 1PH	S1) 0-1500-2000-2500- 2750 VAC @ 1.5A ICAS	46
ARRL-002-200 PLATE XFMR WITH 100/200 VAC 50 HZ PRI		A-0480/ C-CORE	10	100/200 VAC 50 HZ 1PH	S1) 0-1770-2125-2500 VAC @ 1.5A ICAS	46
ARRL-003 SPECIAL FOR WIRELESS INDUSTRY ASSN	PWDP13019	A-0480/ C-CORE	10	235 VAC 60 HZ 1PH	S1) 0-1900-2100-2600- 2800 VAC @ 1.5A ICAS	46
B&W PT-2500A PLATE XFMR (ER) REWIND USING OLD MOUNTING HARDWARE		EI-200 X 4.5" 29GAM6	4	0-120-148 & 0-120-148 VAC 60 HZ 1 PH	S1) 1375 VAC @ 0.8A CCS	40
B&W PT2500A ER FILAMENT XFMR EXACT REPLACEMENT TRANSFORMER	PWDF13103	EI-125 X 2" 29GAM6X	2	15/230 VAC 60 HZ 1 PH	S1) 90 VAC @ 60 MA CCS S2) 6.3 VAC @ 1A CCS S3) 5.2 VCT @ 30A CCS	7
B&W PT2500A FIL & IND POWER FOR CONVERSION TO SINGLE 3CX1200A7		EI-150 X 2	4	115/230 VAC 60 HZ 1 PH	S1) 115 VAC @ 0.1A CCS S2) 6.0 VAC @ 1.0A CCS S3) 7.5 VCT @ 21A CCS	10
B&W PT2500A FILAMENT XFMR LARGER THAN ORIGINAL (EI-125 X 2" SN-2)		EI-150 X 2	4	115/230 VAC 60 HZ 1 PH	S1) 90 VAC @ 0.1A CCS S2) 6.3 VAC @ 1.0A CCS S3) 5.2 VCT @ 30A CCS	10
B&W PT2500A7 OUTBOARD PLATE FOR SINGLE 3CX1200A7 CONVERSION		A-518 C-CORE	10	115/230 VAC 60 HZ 1PH WITH HI/LO TAPS	S1) 1485/1143 VAC @ 2.75A CCS	66
BC-610 LV FIL/BIAS XFMR T1	PWDP13194	EI-150 X 2.5" 29GM6X	4	117 VAC 60 HZ 1 PH	S1) 1000 VCT @ 220 MA CCS S2) 5.0 VAC @ 3A CCS S3) 2.5 VCT @ 5A CCS	12
BTI LK-2000 PLATE FOR BRAD THOMPSON INDUSTRIES LK-2000		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	1250 VAC @ 1.5A CCS	46
BTI LK-2000 PLATE/FILAMENT COMBINATION PLATE & FILAMENT TRANSFORMER		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 1250 VAC @ 1.5A CCS S2) 7.5 VCT @ 21A CCS	46
CENTRAL ELECTRONICS 100V CH CH-1 OR CH-2 DC CHOKE, CHICAGO 29372		EI-100 X 1	1	5-16 HY @ 250MA ICAS (80 OHMS DC)		2
CENTRAL ELECTRONICS 100V PWR T-1 SUPPLIES +600, +340, -120 VOLTS DC		EI-175 X 2.5 29GA M6	5	115 VAC 60 HZ 1 PH	S1) 762-450-0-94-450- 762 VAC @ 250MA CCS S2) 5.0 VAC @ 3A CCS S3) 12.6 VCT @ 7A CCS S4) 6.3 VAC @ 3.6A CCS	17

Description	Hammond Part Number	Core	Style (see above)	Style		Approx. Weight (lbs)
				Primary	Secondary	
CENTRAL ELECTRONICS 600L FILAMENT MULTIPLE FILAMENT, CHICAGO 25077	PWDF13181	EI	4	120 VAC 60 HZ 1 PH	S1) 240 VAC @ 0.015 A S2) 10 VCT @ 5 A CCS S3) 6.3 VAC @ 0.45 A CCS S4) 6.3 VAC @ 0.3 A CCS S5) 2.5 VCT @ 4 A CCS (2,500 VDC INSULATION) S6) 6.3 VCT @ 4 A CC	10
CHOKE 10 HY @ 0.35A DC STYLE #4 VERT BRKT WSCREW LUGS ON COIL		EI-150 X 2	4	10 HY @ 350 MA DC (650 WVDC)		10
CHOKE 10 HY @ 0.5A DC FOR 600 VDC @ 500 MA POWER SUPPLY		EI-175 X 2	4	10 HY @ 0.5A DC (600 WVDC)		14
CHOKE 10.0 HY @ 1.0A DC 3000 WVDC, 10 KVDC INSULATION		A-0274/ C-CORE	10	10.0 HY @ 1.0A DC		37
CHOKE 10.0 HY @ 1.3A DC 4000 WVDC 1 PH (10 KVDC TEST)		A-0525/ C-CORE	9	10.0 HY @ 1.3A DC		49
CHOKE 15.0 TO 5.0 HY @ 1.5A SWINGING CHOKE, 6000 WVDC, 10 KVDC INS		A-518 C-CORE	10	15.0 HY @ 0.15A TO 5.0 HY @ 1.5A DC		66
CHOKE 16.0 HY @ 0.25A DC 1 PH CHOKE FOR 1500 VDC SUPPLY, 5KV TEST		A-0036/ C-CORE	10	16.0 HY @ 0.25A CCS		7
CHOKE 16.0 HY @ 0.4A DC 1500 WVDC, 5 KVDC TEST		A-0016/ C-CORE	10	16.0 HY @ 0.4A DC		17
CHOKE 25.0 TO 5.0 HY @ 0.5A SWINGING CHOKE, 1500 WVDC, 10 KV INS		EI-162 X 3.5	2	25.0 HY @ 0.1A TO 5.0 HY @ 0.5A		24
CHOKE 25.0 TO 5.0 HY @ 1.5A SWINGING CHOKE, 4000 WVDC, 10 KV INS		A-530 C-CORE	9	25 HY @ 0.2A TO 5.0 HY @ 1.5A		71
CHOKE 30.0 TO 5.0 HY @ 1.0A SWINGING CHOKE FOR 3000 VDC 1PH SUPPLY		A-0518/ C-CORE	9	30 HY @ .125A TO 5.0 HY @ 1.0A DC		38
CHOKE 8.0 HY @ 0.175A DC LV DC FILTER CHOKE, 3 KVDC TEST		EI-100 X 1	1	8.0 HY @ 175 MA DC		2
CHOKE 8.0 HY @ 0.3A 2.5 KV TEST, 800 WVDC		EI-125 X 2	2	8.0 HY @ 0.3A DC (800 WVDC)		7
CHOKE 8.0 HY @ 1.5A 10 KVDC INSULATION, 3000 WVDC		A-0480/ C-CORE	10	8.0 HY @ 1.5A DC (3000 WVDC)		46
CHOKE 8.0 HY @ 1.5A 4000 WVDC	PWDI13169	EI	2	8.0 HY @ 1.5A DC (4000 WVDC)		63
CHOKE 8.0 HY @ 2.0A 10 KVDC INSULATION, 5200 WVDC 1PH		A-540 C-CORE	9	8.0 HY @ 2.0A DC (5200 WVDC 1PH)		92
CHOKE 9.0 HY @ 0.25A DC RESONATE WITH 0.2 MFD CAP @ 120 HZ		A-0036/ C-CORE	10	9.0 HY @ 0.25A DC (1500 WVDC 1 PH)		7
CHOKE 9.0 HY @ 0.65A DC 4000 WVDC RESONATE WITH 0.2 MF 10 KV CAP		A-0393/ C-CORE	10	9.0 HY @ 0.65ADC (4000 WVDC 0.2 MF CAP)		23
CHOKE 9.0 HY @ 1.0A DC 4000 WVDC RESONATE WITH 0.2 MF 10 KV CAP		A-0274/ C-CORE	10	9.0 HY @ 1.0A DC (4000 WVDC 0.2 MF CAP)		37
CHOKE 9.0 HY @ 1.0A DC HP SLIM & TALLER VERSION		A-0518/ C-CORE	9	9.0 HY @ 1.0A DC (4500 WVDC)		38
CHOKE 9.0 HY @ 1.5A DC 5000 WVDC RESONATE WITH 0.2 MF 10 KV CAP		A-0518/ C-CORE	10	9.0 HY @ 1.5A DC (5000 WVDC 0.2 MF CAP)		66
CHOKE 60 HY @ 150 ma. DC MODULATION REACTOR (CHOKE)	PWDI13132	EI	4	60 HY @ 150 ma. DC CCS (2 KVDC TEST)		10
CLEGG APOLLO SIX T1 POWER T1 MAIN POWER XFMR, P/N 601-016		EI-175 X 2.5" 29GAM6	6	117 VAC 60 HZ 1 PH	S1) 1050 VAC @ 0.5A ICAS S2) 380 VCT @ 0.1A ICAS	17

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
COLLINS KW-1 AUDIO DRIVER PP 6B4G PLATES TO PP 810 GRIDS (T-404)	PWDM13041	EI-100 X 1	5	375 VCT @ 0.1A CCS (5000 OHMS P-P CT)	S1) 125 VAC @ 0.1A CCS (2225 OHMS G-G CT) S2) 125 VAC @ 0.1A CCS (2225 OHMS G-G CT)	2
COLLINS KW-1 BIAS T-401 -150 VOLT DC BIAS & FILAMENT TRANSFORMER	PWDP13188	EI-112 X 1.125	4	115 VAC 60 HZ 1 PH	S1) 300 VCT @ 30 MA CCS S2) 5 VAC @ 2A CCS	3
COLLINS KW-1 LV POWER T-402 LV POWER (300 VDC @ 325 MA) & FIL WNDGS		EI-175 X 2" 29GAM6X	5	115 VAC 60 HZ 1 PH	S1) 400-80-0-80-400 VAC @ 325 MA CCS S2) 5.0 VAC @ 6A CCS S3) 5.0 VAC @ 2A CCS S4) 6.3 VCT @ 7A CCS	14
COLLINS KW-1 MODULATION XFMR PP 810 MODULATORS TO PARALLEL 4-250A'S	PWDP13133	A-0480 / C- CORE 29GAM6X	10	115/230 VAC 60 HZ 1 PH	S1) 5800 VCT @ 0.7A CCS	46
COLLINS KW-1 RECT FIL ER T-501 872A FIL XFMR (EXACT REPLACEMENT)	PWDF13255	EI-150 X 1.25" 29GRH	5	115 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 15A CCS (10 KVDC INS)	6
COLLINS KW-1 RECT FILAMENT T-501 872A FILAMENT TRANSFORMER		EI-150 X 1.5	5	115 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 15A CCS (10 KVDC INS)	8
COLLINS KW-1 SPLATTER CHOKE L503, MODIFIED FOR 0.25-1.2 HY @ 0.5A DC		EI-150 X 2.5" 29G M6	7	0-.25-.40-.52-.62-.76-.93- 1.2 HY @ 0.5A		12
COLLINS KWS-1 HV CHOKE L-501 - Direct Replacement "EI" Lamination 8 HY @ 0.5A DC TUNED CHOKE REQUIRES THE 0.15 MFD RESONATING CAP		EI	2	8.0 HY @ 0.5A DC (4000 WVDC, 55 OHMS DC)		20
COLLINS KWS-1 HV CHOKE L-501 8 HY @ 0.5A DC TUNED CHOKE REQUIRES THE 0.15 MFD RESONATING CAP		A-0274/ C- CORE	9	8.0 HY @ 0.5A DC (4000 WVDC, 55 OHMS DC)		21
COLLINS KWS-1 HV FILAMENT REPLACEMENT 866A FIL XFMR (T-502) - BOBBIN WOUND - EPOXY FILLED BAYS	PWDF13061	EI-087 X 1	7	115/230 VAC 50/60 HZ 1 PH	S1) 2.5 VCT @ 10A CCS (10 KVDC TEST)	2
COLLINS KWS-1 LV DC CHOKE +275 VDC FILTER CHOKES, L-502 & L-504		EI-112 X 1.125	5	4 HY @ 230MA DC (+275 WVDC)		3
COLLINS KWS-1 LV POWER XFMR T-506 P/N 662-0146-00 ORIGINAL WAS STYLE #07 - CAN IS NO LONGER AVAILABLE	PWDP13171	EI-150 X 2.5" 29GAM6	5	120 VAC 60 HZ 1 PH	S1) 420-200-0-200-420 VAC @ 0.255A CCS S2) 5.0 VAC @ 4A CCS S3) 12.6 VAC @ 0.3A CCS S4) 6.3 VAC @ 9.0A CCS	13
COLLINS KWS-1 PLATE XFMR P/N 662-0155-00, E-5017		A-0518/ C- CORE	9	115/230 VAC 60 HZ 1 PH	4800 VCT @ 800 MA CCS	38
COLLINS KWS-1 PLATE XFMR P/N 662-0155-00, E-5017	PWDP13082	EI 29GAM6	9	115/230 VAC 60 HZ 1 PH	S1) 4800 VCT @ 800 MA CC	39
COLLINS KWS-1 SCREEN P/N 662-0157-00 T504 - REPLACEMENT IS NOT POTTED - SEE PDF DRAWING	PWDP13043	EI-100 X 1.25 29GAM6	5	120 VAC 60 HZ	S1) 980 VCT @ 0.050A CCS	6
COLLINS KWS-1 SCREEN FIL SCREEN SUPPLY FILAMENT XFMR (T-505)		EI-112 X 1.125	5	115 VAC 60 HZ 1 PH	S1) 6.3 VAC @ 3.0A CCS S2) 5.0 VAC @ 2.0A CCS	3
COLLINS PM-2 POWER XFMR P/N 662-0033-00, BALLASTAN #BC-2950		EI-137 X 2	4	115/230 VAC 60 HZ 1PH	S1) 325 VRMS @ 400 MA CCS S2) 230 VRMS @ 150 MA CCS S3) 110 VRMS @ 15 MA CCS S4) 6.3 VAC @ 6A CCS	8
COLLINS 21E LV CHOKE L114 LV DC FILTER CHOKE, P/N 668-0072-00	PWDI13191	EI-175 X 3"	4	20 HY @ 0.35 A DC		19

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
COLLINS 30K MODULATION XFMR P/N 677-0316-00, 200W,+/- 2DB 100-5000HZ	PWDM13203	EI-150 X 2.5" 29GM6X	7	2450 VCT @ 175 MA (32K OHMS)	S1) 1770 VAC @ .150ADC & .113AAC(16.7K OHM) S2) 248 VAC @ .050ADC	12
COLLINS 30K PLATE 4-125A RF PA & PP 75T MODULATORS	PWDP13256	A-0480/ C- CORE	10	115/230 VAC 60 HZ 1PH	2950-2365-0-2365-2950 VAC @ 750MA CCS	46
COLLINS 30K-1 FILAMENT T403 2 EA 75TH'S & 1 EA 4-125A (CASED UNIT)		EI-125 X 1.75	7	0-105-110-115 VAC 60 HZ 1 PH	5.0 VCT @ 20A CCS	6
COLLINS 30K-1 HD PLATE HEAVY DUTY REPLACEMENT TRANSFORMER		EI-250 X 4" 29G M6X	4	115/230 VAC 60 HZ 1 PH	2950-2365-0-2365-2950 VAC @ 350 MA CCS	53
COLLINS 30K-5 HIPERSIL PLATE REPLACES P/N 662-0127-00 (SAME MTG)		A-0480/ C- CORE	10	115/230 VAC 60 HZ 1PH	2950-2365-0-2365-2950 VAC @ 0.4A CCS	46
COLLINS 30K-5 RECT FIL ER CASED REWIND P/N 672-0079-00		EI-100 X 1.5	4	0-105-110-115 VAC 60 HZ 1 PH	2.5 VAC @ 10A CCS	3
COLLINS 30L-1	PWDP13170	EI-175 X 3" 29G M6X	2	115/230 VAC 50/60 HZ 1 PH	S1) 650 VAC 0.7A CCS S2) 120 VAC @ 0.020A CCS S3) 6.3 VCT @ 16A CCS	19
COLLINS 30L-1-1 MODIFIED SEC 1 VOLTS & SEC 2 CURRENT		EI-175 X 3" 29G M6X	2	115/230 VAC 50/60 HZ 1 PH	S1) 550 VAC 0.7A CCS S2) 120 VAC @ 0.100A CCS S3) 6.3 VCT @ 16A CCS	19
COLLINS 30S-1 ALC XFMR T-102 1:1 RATIO ALC TRANSFORMER		EE 24-25 SQ STACK	1	3.5 HY @ 700 OHMS		
COLLINS 30S-1 BIAS P/N 662-0353-00	PWDP13042	EI-087 X 1	1	115 VAC 50/60 HZ 1 PH	S1) 125 VCT @ 0.1A CCS S2) 12.6 VAC @ 0.8A CCS	2
COLLINS 30S-1 CHOKE REPLACEMENT FOR L-202		EI-175 X 3	5	8.0 HY @ 0.5A DC (10 KVDC INS)		19
COLLINS 30S-1 ER RECT FIL T-202,P/N 662-0352-00 REPLACEMENT	PWDP13018	EI-100 X 1.25 29GAM6	5	15 VAC 60 HZ 1 PH	S1) 2.5 VCT @ 10A CCS (10 KVDC INSULATION)	3
COLLINS 30S-1 FILAMENT--T101 LOW CAPACITY RF PA FILAMENT TRANSFORMER		EI-150 X 1.5	4	105 VAC 60 HZ 1 PH	6.0 VAC @ 12.5A LOW CAPACITY	8
COLLINS 30S-1 FILTER CHOKE HEAVY DUTY HIPERSIL DC CHOKE - L202		A-0016/CA- 16	10	8.33 HY @ .5A CCS (3000 WVDC 1PH FWCT)		17
COLLINS 30S-1 FILTER CHOKE-1 FOR 50 HZ WITH 0.15 MFD CAP (L202)		A-0016/ C- CORE	10	16.7 HY @ .5A CCS (3000 WVDC 1PH FWCT)		17
COLLINS 30S-1 PLATE XFMR STANDARD REPLACEMENT TRANSFORMER	PWDP13017	EI-300 X 3.375	4	115/230 VAC 60 HZ 1PH HI-LO TAPS	S1) 6320 VCT @ 350MA CCS (HI Primary Tap) S2) 245 VAC @ 350MA CCS (HI Primary Tap)	67
COLLINS 30S-1 RECT FILAMENT T-202, P/N 662-0352-00		EI-100 X 1	5	115 VAC 60 HZ 1 PH	2.5 VCT @ 10A CCS (10 KVDC INSULATION)	2
COLLINS 30S-1 SCREEN CHOKE L-201, P/N 668-0356-00, STD SCREEN CHOKE		EI-150 X 1.5	5	3.5 HY @ 500 MA DC (300 WVDC SUPPLY)		8
COLLINS 30S-1 SCREEN POWER 350/250 VAC @ 400 MA CCS	PWDP13149	EI-175 X 1.75	4	115 VAC 60 HZ 1PH HI- LO TAPS	S1) 350 VAC @ 400 MA CCS	12
COLLINS 30S-1-J PLATE XFMR JAPANESE 100/200 VAC 50 HZ PRIMARY		EI-300 X 3.375	4	100/200 VAC 50/60 HZ 1PH HI-LO TAPS	S1) 6320 VCT @ 350MA CCS S2) 245 VAC @ 350MA CCS	67
COLLINS 30S-1-50 PLATE XFMR 50 HZ VERSION OF 30S-1 PLATE XFMR	PWDP13124	EI-300 X 3.375	4	115/230 VAC 50/60 HZ 1PH HI-LO TAPS	S1) 6320 VCT @ 350MA CCS S2) 245 VAC @ 350MA CCS	67

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
COLLINS 30S-1M PLATE XFMR 120 VAC MORE SCREEN VOLTS THAN STD 30S-1		EI-300 X 3.375	4	115/230 VAC 60 HZ 1PH HI-LO TAPS	S1) 6320 VCT @ 350MA CCS S2) 365 VAC @ 350MA CCS	67
COLLINS 30S-1M-J PLATE XFMR SPECIAL 100/200 VAC 50/60 HZ PRIMARY		EI-300 X 3.375	4	100/200 VAC 50 HZ 1PH HI-LO TAPS	S1) 6320 VCT @ 350MA CCS S2) 365 VAC @ 350MA CCS	67
COLLINS 30S-1M-50 PLATE XFMR 50 HZ VERSION OF 30S-1M PLATE XFMR		EI-137 X 1.375	4	220 VAC 60 HZ 1 PH	S1) 120 VAC @ 500 MA CCS	6
COLLINS 310B POWER XFMR BIAS/LV/HV/FILS FOR COLLINS 310B EXCITER		EI-150 X 2	6	115 VAC 60 HZ 1 PH	S1) 1360 VCT @ 60 MA CCS S2) 600/150 VCT @ 70 MA CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS S5) 6.3 VAC @ 4A CCS	10
COLLINS 32V-1/2/3 LV POWER LV POWER XFMR FOR 32V-1, 32V-2 OR 32V-3	PWDP13005	EI-150 X 1.5	4	115 VAC 60 HZ 1 PH	S1) 850 VCT @ 175 MA CCS S2) 5.0 VAC @ 4A CCS S3) 5.0 VAC @ 4A CCS S4) 6.3 VAC @ 9A CCS	8
COLLINS 32V-1/2/3 LV PWR ER LV POWER XFMR FOR 32V-1, 32V-2 OR 32V-3- original case not available, will be supplied as style 4		EI-125 X 1.75 29GAM6	7	115 VAC 60 HZ 1 PH	S1) 850 VCT @ 175 MA CCS S2) 5.0 VAC @ 4A CCS S3) 5.0 VAC @ 4A CCS S4) 6.3 VAC @ 9A CCS	6
COLLINS 32V3 HV POWER TRANSFORMER T302, P/N 662-0014-00		EI-162 X 2	4	115 VAC 50/60 HZ 1 PH W/VCTAP	S1) 1370 VCT @ 500 MA CCS	15
COLLINS 51J2 POWER ER CASE (case no longer available) ER CASE, P/N 672-0575-00, 472-0326-00		EI-137 X 1.375	7	115/230 VAC 60 HZ 1 PH	S1) 700 VCT @ 125 MA CCS (FWCT) S2) 5.0 VAC @ 2A CCS S3) 6.3 VAC @ 5A CCS	9
COLLINS 51J4 POWER ALSO USED IN COLLINS R-388 (51J-3) RECEIVER	PWDP13063	EI-150 X 1.5	4	115/230 VAC 45/70 HZ 1 PH	S1) 700 VCT @ 200 MA CCS (FWCT) S2) 5.0 VAC @ 2A CCS S3) 6.3 VAC @ 7A CCS	8
COLLINS 51J4 POWER ER CASE (case no longer available see part above) ER CASE, P/N 672-0575-00		EI-125 X 1.5" 29GAM6	7	115/230 VAC 60 HZ 1 PH	S1) 700 VCT @ 125 MA CCS (FWCT) S2) 5.0 VAC @ 2A CCS S3) 6.3 VAC @ 5A CCS	10
COLLINS 516F-1 POWER XFMR P/N 662-0252-00 MODEL 164	PWDP13075	EI-150 X 1.5	5	115 VAC 60 HZ 1PH	S1) 920-0-920 VAC @ 250MA ICAS	8
COLLINS 516F-2 CHOKE (L1/L2) 8 HY @ 175MA DC 200 OHMS P/N 668-0300-00		EI-100 X 1	6	8 HY @ 175MA DC		2
COLLINS 516F-2 CHOKE (L3) 1.0 HY @ 180MA DC FILTER CHOKE	PWDI13251	EI-075 X 1	3	1.0 HY @ 180 MA DC		1
COLLINS 516F-2HD POWER P/N 662-0434-00 ADVERTISED UNIT - OLDER VERSION (120 VAC ONLY)	PWDP13199	EI-175 X 3" 29G M6X	2	120 VAC 60 HZ 1 PH	S1) 1000-425-123-0-425- 1000 VAC @ 250MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19
COLLINS 516F-2HD POWER G P/N 662-0249-010 120/240 PRIMARY - NEWER VERSION	PWDP13200	EI-175 X 3" 29 GA M6	2	120/240 VAC 50/60 HZ 1 PH	S1) 1000-425-123-0-425- 1000 VAC @ 250MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
COLLINS 516F-2HD-100 POWER 100 VAC 60 HZ ONLY PRIMARY	PWDP13201	EI-175 X 3" 29GA M6	2	100 VAC 60 HZ 1 PH	S1) 1000-425-123-0-425- 1000 VAC @ 250MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19
COLLINS 62S-1 POWER XFMR T3, P/N 662-0035-00, STANCOR P/N 30064		EI-125 X 2" 29GM6RH	6	115 VAC 60 HZ 1 PH	S1) 315 VAC @ 125 MA CCS S2) 90 VAC @ 100 MA CCS S3) 6.3 VAC @ 6.5A CCS	7
COLLINS 75A-1, 75A-2, 75A-3, 75A-4 (L29) FILTER CHOKE (#1) P/N 668-0020-00	PWDI13161	EI	3	3 HENRY 120 MA DC 600V WORKING VOLTAGE		2
COLLINS 75A-1, 75A-2, 75A-3, 75A-4 (L30) FILTER CHOKE (#2) P/N 668-0019-00	PWDI13158	EI	3	5 HENRY 80 MA DC 600V WORKING VOLTAGE		2
COLLINS 75A-2/3 POWER P/N 662-0017-00 WITH ADDED 234V	PWDP13233	EI-125 X 1.75	5	117/234 VAC 50/60 HZ 1 PH	S1) 700 VCT @ 150 MA CCS S2) 5.0 VAC @ 2.0A CCS S3) 6.3 VAC @ 6.0A CCS	6
COLLINS 75A-4 NB POWER XFMR P/N 662-0431-00		EI-087 X .875	5	117 VAC 60 HZ 1 PH	S1) 135 VAC @ 0.1A CCS S2) 6.3 VAC @ 3A CCS	2
COLLINS 75A-4 POWER P/N 662-0145-00	PWDP13053	EI-125 X 1.75	5	117 VAC 60 HZ 1 PH	S1) 350-160-0-350 VAC @ 150 MA CCS S2) 5.0 VAC @ 2.0A CCS S3) 6.3 VAC @ 6.0A CCS	6
COLLINS 75S-1, 75S-3, 75S-3A POWER XFMR P/N 662-0301-00, T-4 (75S-1), T-8 (75S-3, 75S-3A)	PWDP13115	EI-112 X 1.5	4	117 VAC 50/60 HZ 1 PH	S1) 220 VCT @ 0.1A CCS S2) 6.3 VAC @ 6.0A CCS	4
COLLINS 75S-3B AUDIO OUTPUT P/N 667-0302-00		EI-050 X .5	1	70 VAC 100-3000 HZ 2500 OHMS (PLATE-B+)	S1) 0-2.8-31.3 VAC, 4/500 OHMS @ 1.9 WATTS	
COLLINS 75S-3B, 75S-3C POWER XFMR MAIN POWER XFMR (T-8) P/N 662-0250-010	PWDP13090	EI-112 X 1.5	5	115/230 VAC 60 HZ 1PH	S1) 290 VCT @ 125MA CCS S2) 6.3 VAC @ 5.5A CCS	4
COLLINS 75S-3B-100 POWER 100 VAC 60 HZ PRIMARY ONLY		EI-112 X 1.5	5	100 VAC 60 HZ 1PH	S1) 290 VCT @ 125MA CCS S2) 6.3 VAC @ 5.5A CCS	4
COMMANDER HF-2500 POWER XFMR HEAVY DUTY REPLACEMENT POWER TRANSFORMER	PWDP13011	EI-250 X 4" 29G M6X	2	230 VCT 60 HZ 1 PH	S1) 900 VRMS @ 2.0A ICAS S2) 6.3 VRMS @ 1A CCS	53
COMMANDER HF-2500-50BS XFMR SPECIAL FOR 50 HZ & BRIDGE RECTIFIER		EI-250 X 4" 29G M6X	2	230 VCT 50 HZ 1 PH	S1) 1800 VRMS @ 1.0A ICAS A CCS	53
COMMANDER HF-2500-50S XFMR 50 HZ VERSION		EI-250 X 4" 29G M6X	2	230 VCT 50 HZ 1 PH	S1) 900 VRMS @ 2.0A ICAS S2) 6.3 VRMS @ 1A CCS	53
DENTRON CLIPPERTON-L POWER TRANSFORMER	PWDP13002	EI-162 X 3.5	2	117/234 VAC 60 HZ 1PH	S1) 0-640-1010 VAC @ 600 MA CCS S2) 12 VAC @ 2A CCS S3) 6.3 VAC @ 16A CCS	24
DENTRON CLIPPERTON-L (Late Production) POWER TRANSFORMER MODIFIED (Filament winding includes C.T.) We believe this power transformer was also used in the later CLIPPERTON QRO	PWDP13123	EI-162 X 3.5	2	117/234 VAC 60 HZ 1PH	S1) 0-640-1010 VAC @ 600 MA CCS S2) 12 VAC @ 2A CCS S3) 6.3 VAC C.T. @ 16A CCS	24

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
DENTRON CLIPPERTON-L F CLIPPERTON-L POWER XFMR WITH 110/220 PRI		EI-162 X 3.5	2	110/220 VAC 60 HZ 1PH	S1) 0-640-1010 VAC @ 600 MA CCS S2) 12 VAC @ 2A CCS S3) 6.3 VAC @ 16A CCS	24
DENTRON CLIPPERTON-L-50 50 HZ VERSION	PWDP13001	EI-162 X 3.5 29G M6X	2	117/234 VAC 50 HZ 1PH	S1) 0-640-1010 VAC @ 600 MA CCS S2) 12 VAC @ 2A CCS S3) 6.3 VAC @ 16A CCS	24
DENTRON CLIPPERTON-LX OUTBOARD POWER TRANSFORMER		A-516 C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 0-640-1060 VAC @ 3.0A CCS S2) 12 VAC @ 2A CCS S3) 6.3 VAC @ 16A CCS	58
DENTRON CLIPPERTON-LX-1 HAS 30 AMP HEAVY DUTY FILAMENT WINDING		A-0516/ C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 0-640-1060 VAC @ 3.0A CCS S2) 12 VAC @ 2A CCS S3) 6.3 VAC @ 30A CCS	58
DENTRON DTR-1200L POWER XFMR REPLACEMENT TRANSFORMER		EI-162 X 3.5" 29GM6X	2	117/234 VAC 60 HZ 1 PH	S1) 775 VAC @ 0.8A CCS S2) 10 VAC @ 1.0A CCS S3) 6.3 VCT @ 8A CCS	24
DENTRON DTR-2000L HIPERSIL REPLACEMENT POWER TRANSFORMER		A-0393/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 0-642-1150 VAC @ 0.7A CCS S2) 5.0 VAC @ 11A CCS S3) 12 VAC @ 1.5A CCS	23
DENTRON DTR-2000L-B FOR USE WITH K5WL CONVERSION		A-0203/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 2400 VAC @ 1.0A ICAS S2) 12 VAC @ 1.5A CCS S3) 5.0 VAC @ 11A CCS	30
DENTRON DTR-2000L-B SP 240/250 VAC PRI TAPS ONLY		A-0203/ C-CORE	10	0-240-250 VAC 60 HZ 1 PH	S1) 2400 VAC @ 1.0A ICAS S2) 12 VAC @ 1.5A CCS S3) 5.0 VAC @ 11A CCS	30
DENTRON DTR-2000L-B1 FOR USE WITH K5WL CONVERSION **W/SEC/TAP		A-0203/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 0-1340-2400 VAC @ 1.0A ICAS S2) 12 VAC @ 1.5A CCS S3) 5.0 VAC @ 11A CCS	30
DENTRON DTR-2000L-B2 SPECIAL		A-0203/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 2700 VAC @ 1.0A ICAS (50% DUTY CYCLE) S2) 18 VAC @ 1.5A CCS S3) 5.0 VAC @ 11A CCS	30
DENTRON DTR-2000L-C 13% HIGHER VOLTAGE THAN DTR-2000L		A-0393/ C-CORE	10	234 VAC 60 HZ 1PH	S1) 0-900-1300 VAC @ 0.7A CCS S2) 5.0 VAC @ 11A CCS S3) 12 VAC @ 1.5A CCS	23
DENTRON DTR-2000L-X1 OUTBOARD POWER XFMR FOR DTR-2000L		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-900-1200 VAC @ 2.0A CCS S2) 5.0 VAC @ 11A CCS S3) 12 VAC @ 1.5A CCS	46
DENTRON GLA-1000B		EI-175 X 2	2	115/230 VAC 60 HZ 1PH	S1) 800 VAC @ 0.3A CCS S2) 6.3 VAC @ 6A CCS S3) 12 VAC @ 1A CCS	14
DENTRON GLA-1000B-1 STYLE #4 EI-150 VERSION		EI-150 X 3" 29GAM6X	4	115/230 VAC 60 HZ 1PH	S1) 800 VAC @ 0.3A CCS S2) 6.3 VAC @ 6A CCS S3) 12 VAC @ 1A CCS	14

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
DENTRON GLA-1000B-2 STYLE #4 EI-150 VERSION, 128/256 VAC PRI		EI-150 X 3" 29GAM6X	4	128/256 VAC 60 HZ 1PH	S1) 800 VAC @ 0.3A CCS S2) 6.3 VAC @ 6A CCS S3) 12 VAC @ 1A CCS	14
DENTRON GLA-1000XS OUTBOARD XFMR FOR BRIDGE RECTIFIER		A-480 C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 1945 VAC @ 1.3A CCS S2) 12 VAC @ 1A CCS S3) 6.3 VAC @ 20A CCS	46
DENTRON MLA-2500B POWER TRANSFORMER		EI-162 X 3" 29GAM6X	2	115/230 VAC 50/60 HZ 1 PH	S1) 0-600-800 VAC @ 0.9A CCS S2) 12.6 VAC @ 4.0A CCS S3) 6.3 VAC @ 8A CCS S4) 120 VAC @ 0.1A CCS	21
DENTRON MLA-2500B-X2 SPECIAL OUTBOARD TRANSFORMER		A-0203/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-600-800 VAC @ 1.5A CCS S2) 12.6 VCT @ 4.0A CCS S3) 6.0 VAC @ 15A CCS S4) 120 VAC @ 0.5A CCS	30
DENTRON MLA-2500B-1 MODIFIED MLA-2500B TRANSFORMER	PWDP13249	EI-162 X 3" 29G M6X	2	115/230 VAC 60 HZ 1 PH	S1) 800 VAC @ 0.9A CCS S2) 12.6 VCT @ 4.0A CCS S3) 6.0 VAC @ 9A CCS S4) 120 VAC @ 0.1A CCS	21
DENTRON MLA-2500B-2 MODIFIED SEC #3		EI-162 X 3" 29GAM6X	2	115/230 VAC 60 HZ 1 PH	S1) 0-600-800 VAC @ 0.9A CCS S2) 12.6 VAC @ 4.0A CCS S3) 13.5 VAC @ 4A CCS S4) 120 VAC @ 0.1A CCS	21
DENTRON MLA-2500X OUTBOARD OUTBOARD POWER XFMR FOR MLA-2500B		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-650-900 VAC @ 3.0A CCS S2) 12.6 VAC @ 4.0A CCS S3) 6.3 VAC @ 8.0A CCS	46
DENTRON 160-10L POWER EXACT REPLACEMENT FOR 160-10L AMPLIFIER	PWDP13048	EI-162 X 3" 29GAM6X	4	115/230 VAC 60 HZ 1 PH	S1) 985 VAC @ 1.0A ICAS OR 0.65A CCS S2) 9.5 VAC @ 1.0A CCS S3) 6.3 VCT @ 16A CCS	21
DENTRON 160-10L-X1 POWER OUTBOARD XFMR FOR 8 TUBES (572B)		A-516 C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 1060 VAC @ 3.0A CCS S2) 9.5 VAC @ 1A CCS S3) 6.3 VCT @ 32A CCS	58
DRAKE AC-4 POWER XFMR DRAKE AC-4 POWER SUPPLY USED WITH "4" LINES (T-4, T-4X AND TR-4)	PWDP13137	EI-150 X 3" 29GAM6X	2	120/240 VAC 50/60 HZ 1 PH	S1) 265 VAC @ 750 MA CCS S2) 90 VAC @ 350 MA CCS S3) 95 VAC @ 100 MA CCS S4) 12.6 VAC @ 5.5A CCS	14

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
DRAKE AC-4 50 HZ XFMR 230 VAC 50 HZ VERSION		EI-150 X 3" 29G M6X	2	230 VAC 50 HZ 1 PH		S1) 265 VAC @ 750 MA CCS S2) 90 VAC @ 350 MA CCS S3) 95 VAC @ 100 MA CCS S4) 12.6 VAC @ 5.5A CCS	14	
DRAKE L4B FILAMENT	PWDF13238	EI-137 X 2	6	0-115/0-62-115 VAC 60 HZ 1 PH		S1) 5.0 VCT @ 30A CCS S2) 22 VAC @ 1A CCS	8	
DRAKE L4B-6 DIRECT REPLACEMENT WITH 6 TERMINAL PRI	PWDP13241	EI-212 X 3	2	120/240 VAC 60 HZ 1PH HI-LO TAPS		S1) 1065/780 VAC @ 0.81A CCS	29	
DRAKE L4B-6-1 DIRECT REPLACEMENT WITH 6 TERM 50 HZ PRI		EI-212 X 3	2	120/240 VAC 50/60 HZ 1PH HI-LO TAPS		S1) 780/1065 VAC @ 0.68A CCS	29	
DRAKE L4B-7 and L7 PS DIRECT REPLACEMENT WITH 7 TERMINAL PRI	PWDP13087	EI-212 X 3	2	120/240 VAC 60 HZ 1PH HI-LO TAPS		S1) 1065/780 VAC @ 0.81A CCS	29	
DRAKE L4B-7-SP and L7 PS 1170 VAC SECONDARY WITH 7 TERMINAL PRI - NOTE: REQUIRES POWER SUPPLY AND RF AMP MODS	PWDP13054	EI-212 X 3	2	120/240 VAC 60 HZ 1PH HI-LO TAPS		S1) 1170/878 VAC @ 0.81A CCS	29	
DRAKE L4B-7-1 DIRECT REPL WITH 100/200 VAC 50 HZ 7 TP		EI-212 X 3" 29GM6X	2	100/200 VAC 50 HZ 1PH HI-LO TAPS		S1) 1065/780 VAC @ 0.81A CCS	29	
DRAKE L4B 3CX1200A7 FILAMENT - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS FILAMENT XFMR FOR PETE WARREN CQ ARTICLE		EI-137 X 2	6	0-115/0-62-115 VAC 60 HZ 1 PH		S1) 7.5 VCT @ 21A CCS S2) 22 VAC @ 1A CCS	8	
DRAKE L4B 3CX1200A7 X 2 FIL - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS FIL XFMR FOR 2 EA 3CX1200A7'S IN L4B	PWDF13243	EI-150 X 2.5" 29GM6X	4	0-120/0-62-120 VAC 60 HZ 1 PH		S1) 7.5 VCT @ 42A CCS S2) 22 VAC @ 1A CCS	12	
DRAKE L4B-HVT-0.9 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS SMALL XFMR FOR PETE WARREN CQ ARTICLE		A-0480/ C- CORE	10	0-210-220-230-240-250 VAC 60 HZ 1PH		S1) 2150-2860-3570 VAC @ 0.9A CCS	46	
DRAKE L4B-HVT-0.9 50/60 HZ - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 50 HZ VERSION OF SMALL PETE WARREN XFMR		A-516 C- CORE	10	210-220-230-240-250 VAC 50/60 HZ 1PH		S1) 2150-2860-3570 VAC @ 0.9A CCS	58	
DRAKE L4B-HVT-1.0M - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 3500 VDC @ 1.0A CCS, 5000 VDC @ 0.8A CCS		A-518 C- CORE	10	0-220-240 VAC 60 HZ 1PH		S1) 0-2800-4000 VAC @ 1.0A CCS	66	
DRAKE L4B-HVT-1.8 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS LARGE XFMR FOR PETE WARREN CQ ARTICLE		A-0518/ C- CORE	10	0-210-220-230-240-250 VAC 60 HZ 1PH		S1) 0-2150-2860-3570 VAC @ 1.8A ICAS	66	
DRAKE L4B-HVT-1.8RH - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS MODIFIED SECONDARY TAPS		A-0518/ C- CORE	10	210-220-230-240-250 VAC 60 HZ 1PH		2500-2860-3215-3570 @ 1.8A ICAS	66	
DRAKE L4B-X-6 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 60 HZ STD OUTBOARD PLATE WITH 6 TERM PRI		A-480	10	120/240 VAC 60 HZ HI- LO TAPS		S1) 1065/780 VRMS @ 2.35A CCS	46	
DRAKE L4B-X-6-1 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 50/60 HZ STD OUTBOARD WITH 6 TERM PRI		A-480 C- CORE	10	120/240 VAC 50/60 HZ HI-LO TAPS		S1) 1065/780 VRMS @ 2.35A CCS	46	
DRAKE L4B-X-7 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 60 HZ STD OUTBOARD PLATE WITH 7 TERM PRI		A-0480/ C- CORE	10	120/240 VAC 60 HZ HI- LO TAPS		S1) 1065/780 VRMS @ 2.35A CCS	46	
DRAKE L4B-X-7-1 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 1100 VAC 2.35A CCS SECONDARY		B-0480/ C- CORE	10	120/240 VAC 60 HZ HI- LO TAPS		S1) 1100/805 VRMS @ 2.35A CCS	46	
DRAKE L4B-XB-M - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF MODS FOR USE WITH BRIDGE RECTIFIER		A-480 C- CORE	10	117/234 VAC 60 HZ WITH HI-LO TAPS		S1) 1700/2300 VAC @ 1.0A CCS	46	

Description	Hammond		Style (see above)	Primary	Secondary	Approx. Weight (lbs)
	Part Number	Core				
DRAKE L4B-XB-M1 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS HEAVY DUTY OUTBOARD FOR BRIDGE RECTIFIER	A-0518/ C-	C-CORE	10	0-230-300 VAC 60 HZ HI-LO TAPS	1915/2500 VCT @ 1.2A CCS	66
DRAKE L4B-XB-7 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS BRIDGE RECT OUTBOARD WITH 7 TERM PRI	A-0480/ C-	C-CORE	10	120/240 VAC 60 HZ 1PH HI-LO TAPS	S1) 2400 VAC @ 1.0A CCS	46
DRAKE L4B-XV-7 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 10% HIGHER VOLTS OUT-PLATE W/7 TERM PRI	A-0480/ C-	C-CORE	10	120/240 VAC 60 HZ HI- LO TAPS	S1) 1170/878 VRMS @ 2.14A CCS	46
DRAKE L4B-X2B-SC - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS FOR USE WITH BRIDGE REC & SWINGING CHOKE	A-0518/ C-	C-CORE	10	120/240 & 48/96 VAC 60 HZ 1 PH	S1) 3200 VAC @ 1.2A CCS	66
DRAKE L4B-X3-6 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 3600 VDC @ 1.5A OUTBOARD WITH 6 TERM PRI	A-525 C-	C-CORE	10	120/240 VAC 60 HZ 1 PH HI-LO TAPS	S1) 1500/1125 VAC @ 3.6A CCS	86
DRAKE L4B-X3-7 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 3600 VDC @ 1.5A OUTBOARD WITH 7 TERM PRI	A-525 C-	C-CORE	10	120/240 VAC 60 HZ 1 PH HI-LO TAPS	S1) 1500/1125 VAC @ 3.6A CCS	86
DRAKE L4B-1200A7 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS SPECIAL FOR 3CX1200A7 MODIFICATION	A-0393/ C-	C-CORE	10	117/234 VAC 60 HZ HI- LO TAPS	S1) 0-1300-1400-1500 VAC @ 0.7A CCS	23
DRAKE L7B-X4-7 - NOTE: REQUIRES EXTENSIVE POWER SUPPLY AND RF AMP MODS 3600 VDC @ 1.5A OUTBOARD WITH 7 TERM PRI	A-525 C-	C-CORE	10	120/240 VAC 60 HZ 1PH HI-LO TAPS	S1) 1500/1125 VAC @ 3.6A CCS	86
DRAKE R-4, R-4A, R-4B POWER XFMR T15 POWER XFMR FOR DRAKE R-4, R-4A AND R-4B RECEIVER ONLY	PWDP13202	EI-100 X 1.5" 29GM6X	5	120/240 VAC 50/60 HZ 1 PH	S1) 260 VCT @ 0.15A CCS S2) 12.6 VCT @ 2A CCS	3
DRAKE R-4C POWER XFMR T14 POWER XFMR FOR DRAKE R-4C RECEIVER ONLY	PWDP13178	EI-100 X 1.5" 29GM6X	5	20/240 VAC 50/60 HZ 1 PH	S1) 250 VCT @ 0.13A CCS S2) 26 VCT @ 0.65A CCS S3) 6.3 VAC @ 2A CCS	3
DRAKE 1A POWER TRANSFORMER FOR R.L. DRAKE MODEL 1A RECEIVER	PWDP13210	EI-100 X 1.25 29GM6X	2	115 VAC 60 HZ 1 PH	S1) 525 VCT @ 50 MA CCS S2) 12.6 VAC @ 2A CCS	3
DRAKE 2-C POWER TRANSFORMER EXACT REPLACEMENT	PWDP13219	EI-100 X 1" 29GM6X	5	115/230 VAC 60 HZ 1 PH	S1) 208 VCT @ .075A CCS S2) 22.8 VCT @ 0.4A CCS S3) 13.3 VCT @ 0.8A CCS	2
EICO 720 DC CHOKE L16		EI-100 X 1	1	8.0 HY @ 150 MA DC (600 WVDC)		2
EICO 720 POWER XFMR 90 WATT CW TRANSMITTER POWER TRANSFORMER		EI-150 X 2" 29GM6X	6	PR) 117 VAC 60 HZ 1 PH	S1) 1400 VCT @ 170 MA CCS S2) 5 VAC @ 2A CCS S3) 6.3 VAC @ 3A CCS	10
ELDICO MODEL 1000 FIL/BIAS W/O 866A FIL WINDING (NEED SS 866A'S)		EI-25 X 1.25	5	115 VAC 60 HZ 1 PH	S1) 6.3 VAC @ 6.5A CCS S2) 250 VCT @ 0.1A CCS	4
ENERGY-ONIX CHOKE P/N 376-056	PWDI13257	C-CORE	10		PR) 2.0 HY @ 1.7A DC (6400 WVDC 1 PH)	37

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
GALAXY V POWER TRANSFORMER		EI-175 X 2	2	117 VAC 60 HZ	S1) 860 VAC @ 250 MA CCS S2) 285 VAC @ 175 MA CCS S3) 80 VAC @ 50 MA CCS S4) 24 VCT @ 500 MA CCS S5) 12.6 VAC @ 6A CCS	14
GATES BC-1 MODULATION REACTOR	PWDI13065	C-CORE	10	40 HENRY 600 MA DC 10KV WORKING VOLTAGE		60
GATES/HARRIS CHOKE 476-0420-000	PWDI13211			5H 2 2.5A, 5600 VDC		
GLOBE CHAMPION LV POWER T1 LV, BIAS, FIL VOLTS FOR MODELS 300 & 350	PWDP13217	EI-150 X 2.5" 29GAM6	5	PR) 115 VAC 60 HZ 1 PH	S1) 900 VCT @ 250 MA CCS S2) 110 VAC @ 0.1A CCS S3) 12.6 VCT @ 3A CCS S4) 5 VAC @ 3A CCS S5) 6.3 VCT @ 6A CCS & 6.3 VAC @ 6A CCS S6) 2.5 VCT @ 10A CCS	12
GLOBE CHAMPION 175 POWER T3 THORDARSON P/N T-21P93		EI-150 X 2.5" 29GM6X	5	117 VAC 60 HZ 1 PH	S1) 2150/1000 VCT @ 95/125 MA CCS FWCT	12
GLOBE CHAMPION 300 MOD XFMR PP 809 MODULATORS TO PARALLEL 9909 RF PA		EI-162 X 1.625	4	11,000 OHMS P-P (PP 809'S) (1280 VCT)	2830 OHMS (920 VDC @ 325 MA, 650 VRMS)	13
GLOBE KING 500 MOD PS CHOKE SNC P/N P2822 SWINGING CHOKE CH4		EI-150 X 1.5" 29GAM6	5	25 HY @ 50 MA TO 5 HY @ 300 MA		8
GLOBE KING 500A LV POWER THORDARSON T-21P89		EI-125 X 2	5	115 VAC 60 HZ 1 PH	1160 VCT @ 150 MA CCS	7
GLOBE KING 500A MOD POWER 1000 VDC FOR 811A'S & 400 VDC FOR 6L6G	PWDP13052	EI-162 X 2	2	117 VAC 60 HZ 1 PH	1160-350-0-350-1160 VAC @ 450 MA ICAS	15
GLOBE KING 500A/B MOD XFMR PP 811A'S TO SINGLE 4-250A/4-400A RF PA	PWDM13086	EI-150 X 3.5" 29GM6X	5	1465 VCT @ 0.246A CCS (7400 OHMS P-P)	1275 VAC @ 0.283A CCS (1800 VDC @ .4A)	16
GLOBE KING 500B PLATE 1800 VDC @ 400 MA CCS FWB CHOKE INPUT	PWDP13074	EI-175 X 5	5	115 VAC 60 HZ 1 PH	S1) 4000 VCT @ 400 MA ICAS (FWCT)	31
GLOBE KING 500B PLATE (MODIFIED) 1800 VDC @ 400 MA CCS FWB CHOKE INPUT	PWDP13108	EI-175 X 5	5	120/240 VAC 60 HZ 1 PH		31
GLOBE KING 500B-X PLATE HEAVY DUTY EXTERNAL PLATE TRANSFORMER		A-0274/ C-CORE	10	115 VAC 60 HZ 1 PH	S1) 4400/4000 VCT @ 400 MA CCS (FWCT)	37
GLOBE KING 500C SCREEN CHOKE CH1 SCREEN SUPPLY DC FILTER CHOKE		EI-075 X .75	1	25 HY @ 0.050A DC (400 WVDC)		1
GLOBE SCOUT 65A POWER XFMR WRL MODEL 65A GLOBE SCOUT TRANSMITTER	PWDP13162	EI-150 X 2" 29G M6X	5	115 VAC 60 HZ 1 PH	S1) 1200 VCT @ 0.2A CCS (500 VDC FWCT) S2) 6.3 VAC @ 3.5A CCS S3) 5 VAC @ 3A CCS	10
GONSET G-50 POWER XFMR 6 METER COMMUNICATOR	PWDP13028	EI-137 X 2" 29GAM6X	5	115 VAC 60 HZ 1 PH	S1) 770 VCT @ 250 MA CCS S2) 5.0 VAC @ 3A CCS S3) 6.3 VAC @ 9A CCS	8
GONSET G-76 POWER XFMR T-1, MAIN POWER TRANSFORMER	PWDP13247	EI-175 X 2.5" 29GM6X	6	115 VAC 60 HZ 1 PH	S1) 1300/540 VCT @ 0.3A CCS S2) 5.0 VAC @ 4A CCS S3) 12.6 VAC @ 5A CCS	17
GONSET GSB-100 POWER ADVERTISED UNIT	PWDP13106	EI-150 X 2	4	117 VAC 60 HZ 1 PH	S1) 720-260-0-130-260-720 VAC @ 150 MA CCS S2) 5.0 VAC @ 3A CCS S3) 5.0 VAC @ 3A CCS S4) 6.3 VAC @ 10A CCS	10

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
GONSET GSB-101 ALT PLATE C ALT XFMR ON EI-175 LAMS WITH 117 VAC PRI		EI-175 X 5" 29G M6X	4		117 VAC 60 HZ 1 PH	S1) 3600 VCT @ 500 MA CCS	31	
GONSET GSB-101 ALT PLATE J ALT XFMR ON EI-175 LAMS WITH 220 VAC PRI		EI-175 X 5" 29G M6X	4		220 VAC 60 HZ 1 PH	S1) 3600 VCT @ 500 MA CCS	31	
GONSET GSB-101 ER PLATE C EXACT REPLACEMENT UNIT WITH 117 VAC PRI	PWDP13101	EI-162 X 3.5" 29GM6X	4		117 VAC 60 HZ 1 PH	3600 VCT @ 500 MA CCS	24	
GONSET GSB-101 ER PLATE J EXACT REPLACEMENT UNIT WITH 220 VAC PRI		EI-162 X 3.5" 29GM6X	4		220 VAC 60 HZ 1 PH	S1) 3600 VCT @ 500 MA CCS	24	
GONSET GSB-101 FILTER CHOKE EXACT REPLACEMENT		EI-150 X 2	5		25 HY @ 75 MA TO 5 HY @ 450 MA DC		10	
GONSET GSB-101 PLATE HEAVY DUTY HIPERSIL REPLACEMENT XFMR		A-0203/ C- CORE	10		117 VAC 60 HZ 1 PH	3600 VCT @ 600 MA CCS	30	
GONSET GSB-201 MK IV POWER		EI-175 X 5 29G M-6	4		120/240 VAC 60 HZ 1PH	2500 VAC @ 1.0A ICAS (0.3A CCS)	31	
GONSET GSB-201 POWER ADVERTISED UNIT		EI-175 X 5" 29G M6X	4		120/240 VAC 60 HZ 1 PH	S1) 1705 VAC @ 500 MA CCS	31	
GONSET GSB-201-1 POWER SPECIAL WITH 12.6 V FIL & 540 VCT WNDGS		EI-175 X 5" 29G M6X	4		120/240 VAC 60 HZ 1 PH	S1) 1705 VAC @ 500 MA CCS S2) 12.6 VAC @ 8A CCS S3) 540 VCT @ 0.1A CCS	31	
HALLICRAFTERS FPM-300-MKII POWER TRANSFORMER		EI-150 X 2.5	6		120/240 VAC 60 HZ 1 PH	S1) 1705 VAC @ 500 MA CCS S2) 6.3 VAC @ 20A CCS	31	
GONSET GSB-201-1 POWER SPECIAL WITH 12.6 V FIL & 540 VCT WNDGS		EI-175 X 5" 29G M6X	4		120/240 VAC 60 HZ 1 PH	S1) 1705 VAC @ 500 MA CCS S2) 12.6 VAC @ 8A CCS S3) 540 VCT @ 0.1A CCS	31	
HALLICRAFTERS FPM-300-MKII POWER TRANSFORMER		EI-150 X 2.5	6		PR) PRI "1" 117/234 PRI "2" 18.7 VCT	S1) 215 VAC @ 250MA S2) 320 VAC @ 250MA S3) 12 VAC @ 1A S4) 6.3-0-103 VAC @ 4A- 0-100MA	12	
HALLICRAFTERS HT-30 POWER POWER XFMR FOR HT-30 MARK I EXCITER		EI-150 X 2.5" 29GAM6	6		117 VAC 60 HZ 1 PH	S1) 490-360-0-75-360- 490 VAC @ 0.25A CCS S2) 5 VAC @ 3A CCS S3) 5 VAC @ 3A CCS S4) 6.3 VAC @ 6A CCS	12	
HALLICRAFTERS HT-32 DC CHOKE L-25, P/N 056-300259		EI-087 X 1	1		9.0 HY @ 135 MA DC		2	
HALLICRAFTERS HT-32 MARK I T4 MAIN POWER TRANSFORMER	PWDP13141	EI-175 X 3	6		117 VAC 60 HZ	S1) 880-270-90-0-270- 880 VAC @ 300MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19	
HALLICRAFTERS HT-32A POWER MAIN POWER TRANSFORMER T4	PWDP13245	EI-175 X 3 29G M-6	=6		17 VAC 60 HZ	S1) 880-270-140-0-270- 880 VAC @ 300MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19	
HALLICRAFTERS HT-32B POWER MAIN POWER TRANSFORMER T103		EI-175 X 3	6		0-75-117 VAC 60 HZ	S1) 880-270-140-0-270- 880 VAC @ 300MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19	
HALLICRAFTERS HT-33 SPECIAL		EI-212 X 4	4		120 VAC 60 HZ 1PH	S1) 4500 VCT @ 500MA CCS	38	
HALLICRAFTERS HT-33A PLATE REPLACEMENT (2700 VDC FOR PL-172)		EI-212 X 4.625	4		120 VAC 60 HZ 1 PH	S1) 6000 VCT @ 0.350A CCS (FWCT LC RECT)	43	

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
HALLICRAFTERS HT-33A/B FIL HT-33A OR HT-33B FILAMENT TRANSFORMER		EI-137 X 1.375	5	120 VAC 60 HZ 1 PH	S1) 350 VCT @ 100MA CCS S2) 6.0 VAC @ 7.8A CCS S3) 2.5 VAC @ 10A CCS (10 KVDC INS)	6
HALLICRAFTERS HT-33A/B FIL HT-33A OR HT-33B FILAMENT TRANSFORMER - MODIFIED FOR SOLID STATE RECTIFIERS (2.5 VAC WINDING ELIMINATED)	PWDF13180	EI-137 X 1.375	5	120 VAC 60 HZ 1 PH	S1) 350 VCT @ 100MA CCS S2) 6.0 VAC @ 7.8A CCS	17
HALLICRAFTERS HT-33B CHOKE SWINGING CHOKE FOR HV POWER SUPPLY (L3)		EI-175 X 2.5	5	55 HY @ 0.050A TO 8 HY @ 0.4A DC		17
HALLICRAFTERS HT-33B PLATE REPLACEMENT (2700 VDC FOR PL-172)	PWDP13071	EI-212 X 4.625	4	120 VAC 60 HZ 1 PH	6000 VCT @ 0.350A CCS (FWCT LC RECT)	43
HALLICRAFTERS HT-37 POWER MAIN POWER TRANSFORMER - SAME AS HT-32 MARK 1 (ABOVE)	PWDP13141	EI-175 X 3	6	0-75-117 VAC 60 HZ	S1) 880-270-140-0-270- 880 VAC @ 300MA CCS S2) 6.3 VAC @ 11A CCS S3) 5.0 VAC @ 3A CCS S4) 5.0 VAC @ 3A CCS	19
HALLICRAFTERS HT-41 PLATE 1800 VDC @ 400 MA CCS FROM FWCT RECT		EI-212 X 4	2	117 VAC 60 HZ 1 PH	S1) 4200 VCT @ 400MA CCS (FWCT)	38
HALLICRAFTERS HT-41 SWG CHOK SWINGING CHOKE	PWDI13143	EI-150 X 2.5" 29GM6X	5	25 HY @ 50 MA TO 5 HY @ 450 MA DC		12
HALLICRAFTERS HT-45 BRIDGE		A-516 C- CORE	9	115/230 VAC 60 HZ 1PH	S1) 3500 VRMS @ 0.5A CCS	33
HALLICRAFTERS HT-45 CHOKE HT-45 MARK II-A SWINGING CHOKE (L1)	PWDI13117	EI-150 X 2	4	16 HY @ 50 MA TO 4 HY @ 350 MA DC		10
HALLICRAFTERS HT-45 PLATE TO PRODUCE 2700 VDC @ 400 MA CCS		A-516 C- CORE	9	120/240 VAC 60 HZ 1 PH	S1) 6000 VCT @ 400 MA CCS (FWCT)	33
HALLICRAFTERS P-20A PLATE		EI-212 X 3.5	5	115 VAC 60 HZ -STATIC SHIELD-	3300 VCT @ 350MA DC	34
HALLICRAFTERS P-20A POWER		EI-150 X 2	2	110/220 VAC 50/60 HZ W/+OR-10% BUCK	46 VCT @ 8A CCS 10% BUCK-BOOST	10
HALLICRAFTERS P-26 POWER		EI-175 X 2	5	117 VAC 60 HZ	860-230-0-130-230-860 @ 300MA	14
HALLICRAFTERS PS-150-120 POWER TRANSFORMER FOR HT-44 POWER SUPPLY	PWDP13092	EI-175 X 2	6	117 VAC 60 HZ 1 PH	S1) 630 VCT @ 450 MA CCS S2) 120 VAC @ 20 MA CCS S3) 12.6 VAC @ 4.5A CCS	14
HALLICRAFTERS PS-500A-AC POWER TRANSFORMER, T201		EI-175 X 2.5	6	117/234 VAC 60 HZ 1 PH	S1) 600 VCT @ 0.6A CCS S2) 135 VAC @ 0.05A CCS S3) 12.6 VAC @ 5.0A CCS	17
HALLICRAFTERS SR-2000 PLATE TRANSFORMER (PLATE & SCREEN) VOLTAGES	PWDP13022	EI-175 X 4" 29G M6	2	117/234 VAC HI-LO TAPS 60 HZ 1PH	S1) 1080 VRMS @ 0.91 AMPS CCS S2) 450 VRMS @ 0.070 AMPS CCS	25
HALLICRAFTERS SR-2000 SCREEN SCREEN CHOKE L301		EI-75 SQ.	1	15 HY @ 100MA		1
HALLICRAFTERS SX-117 POWER POWER XFMR FOR SX-117 RECEIVER		EI-100 X 1.25" 29GM6	5	120 VAC 60 HZ 1 PH	S1) 360 VCT @ 0.1A CCS S2) 6.3 VAC @ 6A CCS	3
HALLICRAFTERS SX-28 AUDIO AUDIO OUTPUT	PWDA13083	EI-075 X .75	1	9K OHMS P-P	100/500/5000 OHMS	1

Description	Hammond		Style (see above)	Primary	Secondary	Approx. Weight (lbs)
	Part Number	Core				
HALLICRAFTERS SX-62A POWER T30, MAIN POWER TRANSFORMER		EI-150 X 2	6	117 VAC 60 HZ 1 PH	S1) 520 VCT @ 0.3A CCS S2) 5.0 VAC @ 3.0A CCS S3) 6.3 VAC @ 8.0A CCS	10
HAMMARLUND HQ-100C POWER T-9		EI-112 X 1.5 29M6RH	6	117 VAC 60 HZ 1 PH	S1) 500 VCT @ 90 MA CCS S2) 5.0 VAC @ 2A CCS S3) 6.3 VAC @ 3A CCS	4
HAMMARLUND HQ-145A POWER T13 MAIN POWER TRANSFORMER	PWDP13094	EI-112 X 1.5 29GM6RH	6	115/230 VAC 60 HZ 1 PH	S1) 360 VCT @ 0.1A CCS S2) 6.3 VAC @ 6A CCS	4
HAMMARLUND HQ-180A POWER REPLACES P/N P26305-1, 115 VAC PRI ONLY	PWDP13021	EI-125 X 1.75	6	115 VAC 60 HZ 1 PH	S1) 420 VCT @ 200 MA CCS S2) 6.3 VAC @ 6A CCS	6
HAMMARLUND HQ-180A POWER (FOR OVERSEAS) REPLACES P/N P26305-1	PWDP13165	EI-125 X 1.75 29GAM6	6	220 VAC 50/60 HZ 1 PH	S1) 420 VCT @ 200 MA CCS S2) 6.3 VAC @ 6A CCS	6
HAMMARLUND HX-50 POWER MAIN POWER XFMR, P/N 26726-1 (6DQ5 PA)		EI-150 X 2.5" 29GM6R	6	117 VAC 60 HZ 1 PH	S1) 700-425-20-0-425- 700 VAC @ 200MA CCS S2) 5.0 VAC @ 3A CCS S3) 6.3 VAC @ 10A CCS	12
HAMMARLUND HX-500 POWER T16 MAIN POWER XFMR, P/N K42351-1	PWDP13096	EI-150 X 3	6	117 VAC 60 HZ 1 PH	S1) 900-320-110-0-320- 900 VAC @ 175MA CCS S2) 12.6 VAC @ 1.2A CCS (5 KV TEST) S3) 6.3 VAC @ 10A CCS	14
HAMMARLUND HXL-1 PLATE "EI" REPLACEMENT TRANSFORMER	PWDP13153	EI 29M6	5	120/240 VAC 60 HZ 1 PH	S1) 900 VAC @ 1.0A CCS	30
HAMMARLUND HXL-1 PLATE HIPERSIL REPLACEMENT TRANSFORMER		A-393 C- CORE	10	115/230 VAC 60 HZ 1 PH	900 VAC @ 1.0A CCS	23
HEATH AT-1 POWER XFMR P/N 54-21	PWDP13114	EI-125 X 1.25" 29GM6	5	115 VAC 60 HZ 1 PH	S1) 860 VCT @ 0.1A CCS (FWCT) S2) 5.0 VAC @ 3A CCS S3) 6.3 VAC @ 2A CCS	4
HEATH BR-2		EI-100 X 1.25	5	117 VAC 60 HZ	S1) 440 VCT @ 75MA S2) 5 VAC @ 2A S3) 12.6 VAC @ 0.6A	3
HEATH CHIPPEWA PLATE XFMR REPLACES BASLER ELECTRIC P/N BE-7129		A-0516/ C- CORE	9	115/230 VAC 60 HZ 1 PH	S1) 7000 VCT @ 0.5A ICAS (FWCT)	33
HEATH DX-100 DRIVER AUDIO DRIVER, P/N 51-23		EI-050 X .625	3	2500 OHMS @ 20 MA DC	S1) 2000 OHMS C.T.	
HEATH DX-100 LOW VOLTAGE HEATH P/N 54-31		EI-150 X 2	4	117 VAC 60 HZ	S1) 317-60-0-60-317 VAC @ 250 MA CCS S2) 5 VAC @ 4A (3 KV INSULATION) S3) 5 VAC @ 2A S4) 12.6 VCT @ 4A	10
HEATH DX-100 MOD DX-100 MODULATION TRANSFORMER	PWDM13136	EI-112 X 1.5	5	8000 OHMS PP C.T. 845 VCT	500/2800 O @ 250MA(88W) 500 VAC @ .176A	4
HEATH DX-100 PLATE HEATH P/N 54-30 POTTED TYPE		EI-150 X 2.5	7	117 VAC 60 HZ 1 PH	1830 VCT @ 400 MA ICAS	12
HEATH DX-100 PLATE OF OPEN FRAME VERSION	PWDP13234	EI-175 X 2" 29GM6X	4	117 VAC 60 HZ 1 PH	1830 VCT @ 400 MA ICAS	14
HEATH DX-20 POWER MAIN POWER TRANSFORMER FOR HEATH DX-20	PWDP13109	EI-125 X 1.75	5	117 VAC 60 HZ 1 PH	S1) 1200 VCT @ 120 MA CCS S2) 6.3 VAC @ 2A CCS S3) 5.0 VAC @ 3A CCS	6

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
HEATH DX-35/40 POWER TRANSFORMER	PWDP13105	EI-125 X 1.75 29GAM6	5	117 VAC 60 HZ 1 PH	S1) 750-0-750 VAC @ 150 MA ICAS (FWCT) S2) 6.3 VAC @ 3.25A CCS S3) 5.0 VAC @ 3A CCS S4) 6.3 VAC @ 0.65A CCS	6
HEATH DX-60 POWER STYLE #6 HALFSHELL TYPE XFMR		EI-137 X 2" 29G M6RH	6	115/230 VAC 60 HZ 1PH	S1) 260 VAC @ 500MA CCS S2) 110 VAC @ 30MA CCS S3) 6.3 VAC @ 2A CCS	8
HEATH HA-10 SWINGING CHOKE P/N 46-28	PWDI13230	EI-125 X 4.375	6	50 HY @ 50MA - 5 HY @ 450MA (1500 WVDC)		13
HEATH HA-10 WARRIOR PLATE TO PRODUCE 1500 VDC @ 0.5A CCS FWCT		EI-175 X 4" 29GM6RTM	6	115/230 VAC 60 HZ 1 PH	S1) 3400 VCT @ 0.5A CCS (FWCT)	25
HEATH HA-10 WARRIOR PLATE SP SPECIAL FOR FWCT CAPACITOR INPUT		EI-175 X 4" 29GM6X	6	115/230 VAC 60 HZ 1 PH	S1) 2500 VCT @ 0.7A CCS (FWCT)	25
HEATH HA-14-X HEAVY DUTY OUTBOARD POWER TRANSFORMER		EI-162 X 3" 29G M6X	2	24 VCT 250 HZ (PP TRANSISTOR DRIVEN)	S1) 0-2400-2800 VAC @ 0.5A CCS S2) 120 VAC @ 0.1A CCS	21
HEATH HL-2200 FILAMENT XFMR REPLACEMENT TRANSFORMER (SAME AS SB-220 / SB-221)	PWDF13057	EI-137 X 1.375	5	120/240 VAC 50/60 HZ 1 PH	S1) 5.0 VCT @ 30A CCS S2) 90 VAC @ 0.1A CCS	6
HEATH HL-2200 POWER XFMR SAME EXACT REPLACEMENT FOR SB-220 / SB-221 / HL-2200	PWDP13034	EI	2	117/234 VAC 60 HZ HI- LO TAPS	860/1171 VAC @ 0.7A CCS	23
HEATH HL-2200 PLATE EXTRA HD REPLACEMENT WITH 7 MIL C-CORE (SAME AS SB-220 / SB-221 / HL-2200) REQUIRES MODIFICATION TO CHASSIS	PWDP13026	B-0393/ (SIDE MOUNT)	10	117/234 VAC 60 HZ HI- LO TAPS	S1) 860/1171 VAC @ 1.3A CCS	23
HEATH HP-23A/B POWER XFMR FOR HP-23A OR HP-23B POWER SUPPLY	PWDP13135	EI-137 X 2.5" 29GM6X	6	120/240 VAC 60 HZ 1 PH	S1) 282 VAC @ 0.25A CCS S2) 0-95-125 VAC @ 0.1A CCS S3) 12.6 VCT @ 6A CCS	10
HEATH HP-23A/B-1 POWER XFMR SPECIAL WITH 6.3 VAC 12A FIL WINDING		EI-137 X 2.5" 29GM6X	6	120/240 VAC 60 HZ 1 PH	S1) 282 VAC @ 0.25A CCS S2) 0-95-125 VAC @ 0.1A CCS	10
HEATH HX-10 HD POWER MARAUDER P/N 54-114 STYLE #7 CASED UNIT		EI-162 X 3 29GA M-6X	4	120 VAC 60 HZ	S1) 940-407-111-0-111- 407-940 VAC @ 375 MA S2) 6.3 VAC @ 9A CCS S3) 5 VAC @ 3A CCS S4) 5 VAC @ 3A CCS	21
HEATH IO-102 SCOPE XFMR HEATH P/N 54-258		EI-137 X 2" 29GAM6X	5	120/240 VAC 50/60 HZ 1 PH	S1) 550 VAC @ 50 MA CCS S2) 200 VAC @ 100 MA CCS S3) 26 VAC @ 250 MA CCS S4) 7.88 VAC @ 1A CCS ???? S5) 0.35 VAC @ 1A CCS	8

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
HEATH IO-10 SCOPE POWER P/N 54-105-24		EI-125 X 1.75	2	115/230 VAC 50/60 HZ	S1) 0-325-650-1175-1175.625 @ 60MA,5MA,0.3A S2) 120 VAC @ 60MA S3) 6.3 VAC @ 0.6A S4) 6.3 VCT @ 3.6A	6
HEATH OP-1 SCOPE		EI-125 X 2.625	5	117 VAC 60 HZ	S1) 120 VAC @ 50MA (PURPLE) S2) 180 VAC @ 300MA (RED) S3) 6.6 VCT @ 3A (GREEN) S4) 6.6 VAC @ 2A (BLUE) S5) 0-1840-1841.35 (IMA) (@0.2A) (YELLOW)	9
HEATH P/N 54-130 HO-13 & HO-10 MONITOR SCOPE POWER XFMR	PWDP13126	EI-100 X 1.5	5	117 VAC 60 HZ 1 PH	S1) 1200 VAC @ .005A CCS S2) 0.625 VAC @ 0.3A CCS (5 KVDC INS) S3) 220 VAC @ .050A CCS S4) 6.3 VAC @ 0.6A CCS S5) 6.3 VAC @ 3.6A CCS	3
HEATH P/N 54-884 STEREO POWER AMPLIFIER POWER TRANSFORMER		EI-162 X 3.5" 29G M6	5	120 VAC 60 HZ 1 PH	S1) 125 VCT @ 6A CCS (+ & - 91 VDC) S2) 54 VCT @ 0.5A CCS (+15,-15,+12,+35 VDC) S3) 6 VAC @ 0.5A CCS (METER LIGHTS)	24
HEATH PS-23 DC CHOKE (L1) 6 HY @ 175 MA DC (350/275 VDC)		EI-100 X 1	1	6 HY @ 175 MA DC (350 WVDC)		2
HEATH RX-1 - MOHAWK PLATE SUGGESTED HAMMOND REPLACEMENT PART NUMBER 272JX REQUIRES PLATE DROPPING RESISTOR (1K OHM, 20 WATT) SEE ARTICLE BY JOHN TREICHLER (KJ6SAV) IN ELECTRIC RADIO (AUGUST 2017) ISSUE FOR DETAILS	272JX					
HEATH SB-1000 HD SPECIAL HIGHER VOLTAGE MODEL WITH FIL & LV WDNGS	PWDP13032	EI-212 X 3" 29GAM6X	4	240 VAC 60 HZ 1 PH	S1) 0-1050-1150-1250-1350-1450-1550V @ 0.5A CCS S2) 5.2 VCT @ 15A CCS S3) 10.5 VAC @ 0.5A CCS	29
HEATH SB-1000 POWER XFMR HEATH P/N 54-1061	PWDP13073	EI-175 X 3.5" 29G M6	4	120/240 VAC 60 HZ 1 PH	S1) 1100 VAC @ 0.5A CCS S2) 5.2 VCT @ 15A CCS S3) 10.5 VAC @ 0.5A CCS	22
HEATH SB-200 T-1 MAIN POWER TRANSFORMER - SB-200 / SB-221 60 HZ ONLY	PWDP13227	EI-175 X 3" 29G M-6	2	120/240 VAC 60 HZ 1 PH	S1) 800 VAC @ 500MA CCS S2) 6.3 VCT @ 8A CCS S3) 120 VAC @ 0.1A CCS	19
HEATH SB-200-X OUTBOARD FOR 6 EA 572B TUBES		A-0274/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 800 VAC @ 1.5A CCS S2) 6.3 VCT @ 24A CCS S3) 120 VAC @ 0.100A CCS	37

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
HEATH SB-200-XJ OUTBOARD FOR 6 EA 572B TUBES, JAP PRI		A-0274/ C-CORE	10	100/200 VAC 60 HZ 1 PH	S1) 800 VAC @ 1.5A CCS S2) 6.3 VCT @ 24A CCS S3) 120 VAC @ 0.100A CCS	37
HEATH SB-200-1 HIGHER VOLTAGE MODEL	PWDP13142	EI-175 X 3	2	110/220 VAC 60 HZ 1 PH	S1) 900 VAC @ 500 MA CCS S2) 6.3 VCT @ 8A CCS S3) 120 VAC @ 0.1A CCS	19
HEATH SB-200-800A7 SPECIAL XFMR FOR 3CX800A7 CONVERSION		EI-175 X 3" 29G M-6	2	120/240 VAC 60HZ 1 PH	S1) 1800 VAC @ 0.6A ICAS S2) 13.5 VAC @ 1.5A CCS S3) 120 VAC @ 0.15A CCS	19
HEATH SB-220 - FILAMENT XFMR 50 HZ REPLACEMENT TRANSFORMER		EI-137 X 1.375	5	120/240 VAC 50 HZ 1 PH	S1) 5.0 VCT @ 30A CCS S2) 90 VAC @ 0.1A CCS	6
HEATH SB-220 / SB-221 - FILAMENT XFMR REPLACEMENT TRANSFORMER	PWDF13057	EI-137 X 1.375	5	120/240 VAC 50/60 HZ 1 PH	S1) 5.0 VCT @ 30A CCS S2) 90 VAC @ 0.1A CCS	6
HEATH SB-220 POWER XFMR EXACT REPLACEMENT FOR SB-220 / SB-221 / HL-2200	PWDP13034	EI	2	117/234 VAC 60 HZ HI-LO TAPS	S1) 860/1171 VAC @ 0.7A CCS	23
HEATH SB-220-3-7 EXTRA HD REPLACEMENT FOR SB-220 / SB-221 / HL-2200 REQUIRES CHASSIS MODIFICATION TO INSTALL	PWDP13026	B-0393/ (SIDE MOUNT)	10	117/234 VAC 60 HZ HI-LO TAPS	S1) 860/1171 VAC @ 1.3A CCS	23
HEATH SB-220-X 2-3 TUBE OUTBOARD - POWER TRANSFORMER		A-0480/ C-CORE	10	117/234 VAC 60 HZ WITH HI-LO TAPS	S1) 925/1175 VAC @ 2.13A CCS	46
HEATH SB-220-X2 OUTBOARD - POWER TRANSFORMER (4-6 3-500Z)		A-518 C-CORE	10	117/234 VAC 60 HZ WITH HI-LO TAPS	S1) 925/1175 VAC @ 3.5A CCS	66
HEATH SB-220-X2B OUTBOARD - USE WITH FULL WAVE BRIDGE RECTIFIER		A-518 C-CORE	10	117/234 VAC 60 HZ WITH HI-LO TAPS	S1) 0-1850-2400 VAC @ 1.75A CCS	66
HEATH SB-220-X2BS OUTBOARD - X2 FOR BRIDGE RECT WITH HI/LO SEC TAPS		A-0518/ C-CORE	10	230 VAC 60 HZ 1PH	0-1850-2400 VAC @ 2.0A CCS	66
HEATH SB-221-X 2-3 TUBE OUTBOARD - POWER TRANSFORMER		A-0480/ C-CORE	10	117/234 VAC 60 HZ WITH HI-LO TAPS	S1) 925/1175 VAC @ 2.13A CCS	46
HEATH SB-230 POWER PLATE, BIAS, & FIL POWER FOR 8873	PWDP13015	EI-150 X 3	5	120/240 VAC 60 HZ 1PH	S1) 800 VAC @ 0.4A CCS S2) 95 VAC @ 0.045A CCS S3) 6.3 VAC @ 3.5A CCS	14
HEATH SB-230-HD POWER PLATE, BIAS, & FIL POWER FOR 2 EA 8873		EI-150 X 5" 29G M6X	5	120/240 VAC 60 HZ 1PH	S1) 1100 VAC @ 0.4A CCS S2) 95 VAC @ 0.045A CCS S3) 12.6 VCT @ 4A CCS	23
HEATH SB-610 SCOPE XFMR P/N 54-168, T-601 MONTIOR SCOPE POWER	PWDP13070	EI-100 X 1.5	5	120 VAC 60 HZ 1 PH	S1) 600 VAC @ 0.020A CCS S2) 215 VAC @ 0.050A CCS S3) 6.3 VAC @ 1.5A CCS (5 KVDC TEST) S4) 6.3 VAC @ 2.5A CCS	3

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
HEATH SB-614 SCOPE XFMR P/N 54-182, STATION MONTIOR SCOPE POWER		EI-100 X 1.5" 29GM6X	5	120 VAC 60 HZ 1 PH	S1) 600 VAC @ 0.020A CCS S2) 210 VAC @ 0.050A CCS S3) 6.3 VAC @ 0.6A CCS (5 KVDC TEST) S4) 6.3 VAC @ 0.6A CCS (16 VDC @ 55 MA)	3
HEATH SB-614/620 SCOPE XFMR P/N 54-182, STATION MONTIOR SCOPE POWER	PWDP13099	EI-100 X 1.5" 29GM6X	5	120 VAC 60 HZ 1 PH	S1) 600 VAC @ 0.020A CCS S2) 210 VAC @ 0.050A CCS S3) 6.3 VAC @ 0.6A CCS (5 KVDC TEST) S4) 6.3 VAC @ 0.6A CCS (16 VDC @ 55 MA)	3
HEATH SCOPE P/N 54-25		EI-112 X 1.5	5	117 VAC 60 HZ	S1) 0-390-780 @ 80MA S2) 780-1440 @ 3MA S3) 1440-1440.625 @ 600MA S4) 6.3 VAC @ 3.5A S5) 6.3 VAC @ 0.6A	4
HEATH TX-1 APACHE PLATE HEATH P/N 54-30 POTTED-CUST.SUPPLY CASE		EI-150 X 2.5	7	117 VAC 60 HZ	1830 VCT @ 400 MA ICAS	12
HEATH TX-1 LV POWER APACHE (54-65)		EI-150 X 2.5	4	117 VAC 60 HZ	S1) 300-120-0-120-300 VAC 175MA S2) 5.0 VAC @ 4A S3) 6.3 VAC @ 3.5A S4) 6.3 VAC @ 9.0A S5) 5.0 VAC @ 2.0A	12
HEATH TX-1 MODULATION APACHE HEATH TX-1 APACHE MOD XFMR P/N 51-43		EI-175 X 2	4	11,000 OHMS P-P C.T.	0-500-3000 OHMS @ 250MA DC (175 WATTS)	14
HEATH VHF-1 SENECA POWER P/N 54-73		EI-150 X 2" 29GM6X	5	117 VAC 60 HZ 1 PH	S1) 1600 VCT @ 150 MA CCS S2) 800 VCT @ 100 MA CCS S3) 5.0 VAC @ 2A CCS S4) 5.0 VAC @ 2A CCS S5) 6.3 VAC @ 8A CCS	10
HEATH W4-AM POWER XFMR P/N 54-29, OPTION - Electrically similar substitute - our stock Hammond P/N 374X	374X					
HEATH W5M POWER P/N 54-32 OPTION - Electrically similar substitute - our stock Hammond P/N 379X	379X					
HENRY TEMPO 2000		EI-175 X 4" 29GM6X	2	120/240 VAC 60 HZ 1 PH HI/LO TAPS	980/760 VAC @ 1.0A ICAS	25
HENRY TEMPO 2020 T101 ON SCHEMATIC		A-0036/ C- CORE	10	0-100-110-117/0-100- 110-117 VAC 60 HZ	S1) 330 VAC @ 0.5A CCS S2) 0-80-250 VAC @ 100 MA CCS S3) 0-10-20-23 VAC @ 6A (13.8 VDC PRI) S4) 4.5 VCT @ 250 MA CCS (BASE FEEDBACK)	7

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
HENRY TEMPO 2020 (C) T101 ON SCHEMATIC -- 117 VAC PRI ONLY		A-36 C-CORE	10	117 VAC 60 HZ 1PH		S1) 330 VAC @ 0.5A CCS S2) 0-80-250 VAC @ 100 MA CCS S3) 0-10-20-23 VAC @ 6A (13.8 VDC PRI) S4) 4.5 VCT @ 250 MA CCS (BASE FEEDBACK)	7	
HENRY 1KD-5 POWER XFMR T1, P/N ECA-1111, DIRECT REPLACEMENT	PWDP13033	EI-175 X 3" 29G M6X	4	115/230 VAC 50/60 HZ 1PH		S1) 2250 VAC @ 200 MA CCS S2) 5.0 VCT @ 15A CCS	19	
HENRY 1KD-5X OUTBOARD POWER TRANSFORMER		A-480 C-CORE	10	115/230 VAC 50/60 HZ 1PH		S1) 2250 VAC @ 0.7A CCS S2) 5.0 VCT @ 15A CCS	46	
HENRY 2K CHOKE RESONATES WITH 0.1 MFD 7500 VDC CAP		EI-175 X 4" 29G M6X	4	17.6 HY @ 500 MA CCS (700 MA ICAS)			25	
HENRY 2K CLASSIC	PWDP13016	EI-250 X 3.125	4	115/230 VAC 60 HZ 1PH		S1) 0-2700-3600 VAC @ 0.5A S2) 10 VCT @ 15A	42	
HENRY 2K CLASSIC DC CHOKE L101 HEAVY DUTY REPLACEMENT FOR ECA 5023	PWDI13024	EI-162 X 2.5" 29GM6X	4	8 HY @ 0.8A DC (0.1 MFD 7.5 KVDC CAP)			18	
HENRY 2K FILAMENT BIAS		EI-150 X 2	4	120/240 VAC 60 HZ		S1) 5.5 VCT @ 30A S2) 90 VAC @ 0.1A	10	
HENRY 2K PLATE TRANSFORMER ORIGINAL LAMINATION SIZE AND STEEL CASE IS NO LONGER AVAILABLE	PWDP13155	EI	5	120/240 VAC 60 HZ 1PH		S1) 6000 VCT @ 0.5A CCS (FWCT)	62	
HENRY 2K ULTRA		EI-212 X 4	4	115/230 VAC 60 HZ 1 PH		2400 VRMS @ 0.45A CCS	38	
HENRY 2K-2 MODIFIED	PWDP13221	A-0518/ C-CORE	9	120/240 VAC 60 HZ 1 PH		S1) 3500 VAC @ 0.8A CCS S2) 10.2 VCT @ 15A CCS	38	
HENRY 2K-2 POWER REPLACEMENT POWER TRANSFORMER	PWDP13215	EI	4	120/240 VAC 60 HZ 1 PH		S1) 3500 VAC @ 0.4A ICAS S2) 10.2 VCT @ 15A CCS		
HENRY 2K-2 POWER HIPERSIL CORE TYPE REPLACEMENT XFMR	PWDP13222	A-0480/ C-CORE	9	120/240 VAC 60 HZ 1 PH		S1) 3500 VAC @ 0.4A ICAS S2) 10.2 VCT @ 15A CCS	26	
HENRY 2K-3 DC FILTER CHOKE		EI-19 X 2	4	17.6 HY @ 0.050A DC TO 10 HY @ 0.7A DC			22	
HENRY 2K-3/4 ER PLATE REPLACEMENT POWER TRANSFORMER		EI-250 X 3.125	4	115/230 VAC 60 HZ 1 PH		S1) 3500 VAC @ 0.4A CCS S2) 10.2 VCT @ 15A CCS	42	
HENRY 2K-3/4 PLATE HEAVY DUTY HIPERSIL CORE TRANSFORMER		A-518 C-CORE	9	115/230 VAC 60 HZ 1 PH		S1) 3500 VAC @ 0.6A CCS S2) 10.2 VCT @ 15A CCS	38	
HENRY 2K-3/4-1 PLATE HD HIPERSIL XFMR WITH HI/LO SEC TAP		A-518 C-CORE	9	115/230 VAC 60 HZ 1 PH		S1) 0-3000-3500 VAC @ 0.6A CCS S2) 10.2 VCT @ 15A CCS	38	
HENRY 2K-4 CHOKE EXACT REPLACEMENT (USE WITH 0.1 MFD CAP)		EI-175 X 4 29G M6X	4	10.0 HY @ 500 MA CCS (700 MA ICAS)			25	
HENRY 2K-4-XM SPECIAL OUTBOARD POWER TRANSFORMER		A-516 C-CORE	10	120/240 VAC		S1) 3500 VAC @ 1A CCS S2) 10.2 VCT @ 30A	58	

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
HENRY 2K-4-1 SPECIAL OUTBOARD POWER TRANSFORMER		A-518 C-CORE	10	120/240 VAC 60 HZ 1PH		S1) 4500 VAC @ 800MA S2) 10.2 VCT @ 15A	66	
HENRY 2KD-2 POWER XFMR T1, P/N 70398, DIRECT REPLACEMENT	PWDP13218	EI-212 X 3" 29G M6X	4	115/230 VAC 60 HZ 1PH		S1) 2800 VAC @ 400 MA CCS S2) 10.0 VCT @ 15A CCS	29	
HENRY 2KD-5 POWER XFMR T1, P/N FDN-7497, DIRECT REPLACEMENT	PWDP13121	EI-212 X 3" 29G M6X	4	115/230 VAC 60 HZ 1PH		S1) 0-1780-2250 VAC @ 400 MA CCS S2) 10.0 VCT @ 15A CCS	29	
HENRY 3K ER PLATE EXACT REPLACEMENT, TRIAD P/N 70400		EI-250 X 5" 29GM6XRH	4	230 VAC 60 HZ HI-LO TAP		S1) 3800/2800 VAC @ 600MA CCS	65	
HENRY 3K-A DC FILTER CHOKE RESONATES WITH 0.1 MFD 7500V CAPACITOR		A-0203/ C-CORE	9	10 HY @ 700 MA DC			17	
HENRY 3K-A ER DC CHOKE 804CT REPLACEMENT (USE WITH 0.1 MFD CAP)		EI-175 X 4	9	230 VAC 60 HZ HI-LO TAP		S1) 4000/3000 VAC @ 600MA CCS	38	
HENRY 3K-A PLATE HIPERSIL REPLACEMENT FOR HENRY 3K-A	PWDP13084	A-0518/ C-CORE	9	230 VAC 60 HZ HI-LO TAP		S1) 4000/3000 VAC @ 600MA CCS	38	
HENRY 3K-A-M HEAVY DUTY PLATE TRANSFORMER		A-516 C-CORE	10	230 VAC 60 HZ 1 PH HI-LO TAPS		4000/3000 VAC @ 1.0A CCS	58	
HENRY 3K-A-MC PLATE SPECIAL HENRY 3K-A PLATE WITH SEC TAPS		A-0518/ C-CORE	9	230 VAC 60 HZ 1 PH		0-2800-3500-4000 VAC @ 0.6A CCS	38	
HENRY 3K-CLASSIC X PLATE PLATE XFMR FOR EXPORT MODEL		A-0525/ C-CORE	10	0-200-210-220-230 VAC 60 HZ 1 PH		S1) 0-3000-4000 VAC @ 1.5A ICAS	86	
HENRY 3K-CLASSIC X-1 PLATE PLATE XFMR FOR EXPORT MODEL W/HI/LO PRI		A-0525/ C-CORE	10	230 VAC 60 HZ HI LO-TAP		4000/3000 VAC @ 1.5A ICAS	86	
HENRY 3002A-M PLATE HEAVY DUTY PLATE TRANSFORMER		A-0516/ C-CORE	10	0-220-230-240 VAC 60 HZ 1 PH		0-3000-4400 VAC @ 1.0A CCS	58	
HENRY 4K ULTRA CHOKE		EI-212 X 4	4	4 HY @ 1.5A CCS OR 2.0A ICAS			38	
HENRY 4K ULTRA DC CHOKE RESONANT CHOKE - REQUIRES 0.2 MFD 10 KVDC CAP	PWDI13097	A-0518/ C-CORE	9	9.0 HY @ 1.0A DC (4500 WVDC)			38	
HENRY 4K ULTRA PLATE REPLACEMENT XFMR WITH 20% PRI CUTBACK TAP FOR MODERN PRI VOLTAGES	PWDP13147	EI	4	0-244-294 VAC 60 HZ 1 PH		0-3500-4200 VAC @ 1.0A ICAS	102	
HENRY 4K ULTRA PLATE SPECIAL XFMR WITH 75% PRI CUTBACK TAP		A-0518/ C-CORE	10	0-220-294 VAC 60 HZ 1 PH		0-4200-5000 VAC @ 1.0A ICAS	66	
HENRY 4K ULTRA PLATE (-1) SPECIAL XFMR WITH 75% PRI CUTBACK TAP		A-0518/ C-CORE	10	0-220-294 VAC 60 HZ 1 PH		0-4200-5000 VAC @ 1.0A ICAS	66	
HENRY 4K ULTRA PLATE (-2) 230, 240, 250 VAC & 75% PRI CUTBACK TAP		A-0518/ C-CORE	10	0-230-240-250-294 VAC 60 HZ 1 PH		0-4200-5000 VAC @ 1.0A ICAS	66	
HENRY 4K-2 DC FILTER CHOKE REPLACES TRIAD P/N 16113		EI-175 X 4" 29GA M6X	2	8.8 HY @ 0.7A DC (RESONATE WITH 0.2 MF)			25	
HENRY 4K-2 SCREEN/BIAS XFMR		EI-137 X 1.75	5	230 VAC 60 HZ 1 PH		S1) 0-500-700-900 VAC @ 0.1A CCS S2) 175 VAC @ 0.1A CCS	7	
HENRY 8K ULTRA XHD DC CHOKE EXTRA HEAVY DUTY DC FILTER CHOKE		A-0525/ C-CORE	9	8.0 HY @ 1.5A CCS			49	
HUNTER 2000A POWER TRANSFORMER		A-0459/ C-CORE	9	120/240 VAC 60 HZ 1 PH		S1) 0-450-700-900 VAC @ 1.0A CCS S2) 6.3 VCT @ 16A CCS S3) 6.3 VAC @ 1A CCS	23	
HUNTER 2000B POWER TRANSFORMER		A-0459/ C-CORE	9	120/240 VAC 60 HZ 1 PH		S1) 0-800-860-920 VAC @ 1.0A CCS S2) 6.3 VCT @ 16A CCS S3) 6.3 VAC @ 1A CCS	23	

Description	Hammond		Style (see above)	Primary	Secondary	Approx. Weight (lbs)
	Part Number	Core				
HUNTER 2000C POWER TRANSFORMER		EI-225S X 3"	6	117/234 VAC 60 HZ 1PH	S1) 900 VAC @ 1.0A CCS S2) 7.0 VAC @ 1.0A CCS S3) 6.0 VCT @ 25A CCS	35
HY-GAIN 3750 POWER XFMR STYLE NO. 5 HORIZONTAL ENDBELL TYPE		EI-150 X 2 29 M6	5	0-100-110-120/0-100- 110-120 VAC 60HZ	S1) 0-265-530 VAC @ 0.25A CCS S2) 0-130-260 VAC @ 0.1A CCS S3) 80 VAC @ 0.1A CCS S4) 0-7-14 VAC @ 3.5A CCS S5) 6.3 VAC @ 4.5A CCS S6) 12.6 VAC @ 0.7A CCS	10
JOHNSON ADVENTURER CHOKE SNC P/N S-1501		EI-087 X 1	1	16 HY To 4 HY @ 150 MA DC		2
JOHNSON ADVENTURER POWER VIKING ADVENTURER POWER TRANSFORMER	PWDP13068	EI-125 X 1.75	4	115 VAC 60 HZ 1 PH	S1) 1060 VCT @ 150 MA CCS S2) 6.3 VAC @ 2A CCS S3) 5.0 VAC @ 3A CCS	6
JOHNSON CHALLENGER POWER EFJ P/N 22.1501, T1 MAIN POWER XFMR	PWDP13206	EI-150 X 2	4	115 VAC 60 HZ 1 PH	S1) 1300 VCT @ 275 MA CCS (FWCT) S2) 6.3 VAC @ 5A CCS S3) 5.0 VAC @ 3A CCS	10
JOHNSON DESK KW BIAS T-200 (WILL FIT, BUT NEED NEW MTG HOLES)	PWDP13058	EI-125 X 2	5	115 VAC 60 HZ 1 PH	S1) 300 VCT @ 150 MA CCS S2) 5.0 VAC @ 3A CCS S3) 5.0 VAC @ 3A CCS	7
JOHNSON DESK KW FILTER CHOKE HV FILTER CHOKE, L300		A-0393/ C- CORE	10	6.0 HY @ 800MA DC (2500 WVDC 1 PH)		23
JOHNSON DESK KW MOD PP 810 MODULATORS TO PARALLEL 4-250A'S	PWDM13037	EI-175 EE- STACK	8	1800/2400 VCT, 18000/11600 OHMS PP	1768 VAC @ 283 MA CCS (6250 OHMS RFFPA)	35
JOHNSON DESK KW MOD FILAMENT FILAMENT XFMR FOR PP 810 MODULATORS		EI-137 X 1.375	5	115 VAC 60 HZ 1 PH	10.0 VCT @ 10A CCS	6
JOHNSON DESK KW PLATE P/N P-2126		EI-287 X 5" STACK	5	115/230 VAC 60 HZ 1 PH	2900-2325-0-2325-2900 VAC @ 600 MA CCS	100
JOHNSON DESK KW PLATE (HR) HIPERSIL REPLACEMENT TRANSFORMER	PWDP13051	A-0480/ C- CORE	10	115/230 VAC 60 HZ 1 PH	2900-2325-0-2325-2900 VAC @ 600 MA CCS	46
JOHNSON DESK KW RECT FIL 872A RECTIFIER FILAMENT XFMR, T-301		EI-150 X 2	4	115 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 20A CCS (10 KVDC INSULATION)	10
JOHNSON DESK KW SCREEN T-201, EFJ P/N 22.1069	PWDP13192	EI-125 X 1.25	5	115 VAC 60 HZ 1 PH (HI-LO TAPS)	1350 VCT @ 125MA OR 1060 VCT @ 130MA	4
JOHNSON INVADER 2000 L301 DC FILTER CHOKE, 4-10 HY @ 500 MA DC	PWDI13231	EI-175 X 2	5	10 HY @ 90 MA TO 4 HY @ 500 MA DC		14
JOHNSON INVADER 2000 L302 DC SCREEN CHOKE, 5 HY @ 100 MA DC		EI-87 X .875	1	5 HY @ 100 MA DC (600 WVDC)		2
JOHNSON INVADER 2000 PLATE MAIN PLATE TRANSFORMER		EI-225 X 3" 29G M6X	6	117/234 VAC 60 HZ 1 PH	5000 VCT @ 400 MA ICAS	33
JOHNSON INVADER 2000 SCREEN T-303, SNC P/N P4215, EFJ P/N 22-1643		EI-125 X 2" 29G M6X	4	0-105-117 VAC 60 HZ 1 PH	S1) 1060 VCT @ 130 MA CCS S2) 5.3 VAC @ 2A CCS	7
JOHNSON INVADER 2000 T302 866A HIGH VOLTAGE FILAMENT TRANSFORMER		EI-100 X 1	4	115 VAC 60 HZ 1 PH	S1) 2.5 VAC @ 10A CCS (5 KVDC TEST)	2
JOHNSON THUNDERBOLT DC CHOKE L101 HIGH VOLTAGE DC FILTER CHOKE	PWDI13205	EI-175 X 2	4	25 HY @ 80 MA TO 5 HY @ 500 MA 2200 VDC		14

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
JOHNSON THUNDERBOLT FILAMENT T-102, SNC P/N P3389, EFJ P/N 22.789-1		EI-150 X 1.5	2	115 VAC 60 HZ 1 PH		S1) 5.0 VAC @ 15A CCS (4-400A FILAMENT) S2) 5.0 VAC @ 15A CCS (4-400A FILAMENT) S3) 2.5 VAC @ 10A CCS (866A FILAMENTS)	8	
JOHNSON THUNDERBOLT LV T-103 SCREEN & BIAS TRANSFORMER, P/N 22.1421	PWDP13250	EI-125 X 1.75	4	0-110-120 VAC 60 HZ 1 PH		S1) 783-219-0-219-783 VAC @ 0.1A CCS S2) 5.0 VAC @ 3.0A CCS S3) 6.3 VAC @ 1.6A CCS	6	
JOHNSON THUNDERBOLT PLATE DIRECT REPLACEMENT - PLATE TRANS (SAME AS T-302 - JOHNSON 500 PLATE)	PWDP13046	EI	5	115/230 VAC 60 HZ 1 PH		4800 VCT @ 500 MA CCS	33	
JOHNSON THUNDERBOLT PLATE HIPERSIL REPLACEMENT PLATE TRANS (T-101)		B-0393/ C-CORE	10	115/230 VAC 60 HZ 1 PH		S1) 4800 VCT @ 500 MA CCS	23	
JOHNSON THUNDERBOLT PLATE ER REPLACEMENT PLATE TRANS (T-101)		EI-225RX 3" 29GAM6X	6	115/230 VAC 60 HZ 1 PH		4800 VCT @ 500 MA CCS	33	
JOHNSON VALIANT DRIVER XFMR P/N 22.1286, T4		EI-062 X .75	1	230 OHMS DC (12AU7 AUDIO DRIVER PLATE)		800 OHMS CT (PP 6146 MODULATOR GRIDS)	1	
JOHNSON VALIANT LOW VOLTAGE POWER TRANSFORMER, (T-2) SNC P/N 3068		EI-150 X 2	5	117 VAC 60 HZ		S1) 310-215-0-215-310 VAC @ 250 MA CCS S2) 6.3 VAC @ 12A CCS S3) 2.5 VAC @ 10A CCS S4) 5.0 VAC @ 2A CCS	10	
JOHNSON VALIANT LV CHOKE 5V4 +300 VDC FILTER CHOKE, L-44		EI-100 X 1	3	10 HY @ 100 MA DC (300 WVDC)			2	
JOHNSON VALIANT MOD XFMR EFJ P/N 22.1285, SNC P/N P2998	PWDM13044	EI-125 X 1.5	5	840 VCT @ 0.212A CCS (7300 OHMS P-P)		S1) 450 VCT @ 0.300A CCS (2100 OHMS RF PA)	5	
JOHNSON VALIANT PLATE FOR JOHNSON VALIANT TRANSMITTER		EI-150 X 3.5" 29GM6X	5	120 VAC 60 HZ 1 PH		S1) 1520 VCT @ 400MA CCS	16	
JOHNSON VIKING COURIER CHOKE HV DC FILTER CHOKE	PWDI13055	EI-137 X 2" 29G M6X	5	PR) 10 HY @ 0.35A CCS (1500 WVDC)			8	
JOHNSON VIKING COURIER PLATE TO DELIVER 1500 VDC @ 335 MA	PWDP13056	EI-175 X 3" 29GAM6X	5	115 VAC 60 HZ 1 PH		S1) 3600 VCT @ 237 MA CCS	19	
JOHNSON VIKING II AUDIO DR SNC P/N 1503 EFJ P/N 22.753	PWDA13076	EI-62 SQ.	3	100 VAC @ .030A CCS (SINGLE 6AU6 PLATE)		S1) 84 VCT @ .036A CCS (PP 807 GRIDS)	1	
JOHNSON VIKING II AUDIO DR-1 SNC P/N 1503 EFJ P/N 22.753 * NO AIR GAP		EI-62 SQ.	3	100 VAC @ .030A CCS (SINGLE 6AU6 PLATE)		84 VCT @ .036A CCS (PP 807 GRIDS)	1	
JOHNSON VIKING II HV XFMR SNC P/N #1781, EFJ P/N 23.1002-1		EI-150 X 2	5	115 VAC 60 HZ 1 PH		865-0-865 VAC @ 250MA CCS	10	
JOHNSON VIKING II LV POWER T-2, P/N 22.752, P/N P1893	PWDP13225	EI-125 X 2	5	115 VAC 60 HZ 1 PH		S1) 298-70-0-70-298 VAC @ 250MA CCS S2) 6.3 VAC @ 7A CCS S3) 5 VAC @ 2A CCS S4) 5 VAC @ 2A CCS	7	
JOHNSON VIKING II MOD XFMR T4, SNC P/N P1992 PP 807'S TO PAR 6146	PWDM13220	EI-112 X 1.875	5	795 VCT @ 100 MA PP 807 @ 7000 OHMS P-P		S1) 500 VAC @ 250 MA DC (RP = 2800 OHMS)	5	
JOHNSON VIKING RANGER CHOKE P/N 22.749, SNC P/N P1501, LV DC CHOKE	PWDI13014	EI-087 X 1	1	15.0 HY @ 95 MA DC (DCR = 290 OHMS)			2	
JOHNSON VIKING RANGER AUDIO DR SNC P/N 1503 EFJ P/N 22.753	PWDA13076	EI-62 SQ	3	100 VAC @ .030A CCS		S1) 84 VCT @ .036A CCS (PP 1614 / 6L6 GRIDS)	1	
JOHNSON VIKING RANGER II MOD SNC P/N P2429, T2, PP 7027A'S, 32 WATTS	PWDM13007	EI-087 X 1	1	10600 OHM PP, 695 VCT @ .072A CCS		S1) 19.8 VAC @ 0.050A CCS (4% FEEDBACK) S2) 495 VCT @ .065A AC & .130A DC	2	

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
JOHNSON VIKING RANGER PLATE SNC P/N 2793, EFJ P/N 22.985	PWDP13183	EI-150 X 2.5	5	117 VAC 60 HZ	S1) 670-420-140-0-140-420-670 VAC @ 0.260A S2) 6.3 VAC @ 10A CCS S3) 5.0 VAC @ 3A CCS	12
JOHNSON VIKING 500 HD PLATE HD PLATE ** NEED HIGHER COVER ON PS		A-0274/ C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 4800 VCT @ 500 MA CCS	37
JOHNSON VIKING 500 L302 10 HY @ 200MA, P/N 22.1264	PWDI13131	EI-112 X 1.5	2	10 HY @ 200MA DC (350 WVDC)		4
JOHNSON VIKING 500 L303 EFJ P/N 22.1265 25HY@.08A TO 5 HY @ 0.5A	PWDI13036	EI-175 X 2" 29GAM6X	5	25 HY @ 80 MA TO 5 HY @ 0.5A * 2200 VDC		14
JOHNSON VIKING 500 MOD VIKING 500 MODULATION TRANSFORMER	PWDM13062	EI-212 X 3	4	23000 OHMS P-P 2400 VCT (200-3500 HZ)	S1) 8000 OHMS (2000VDC @ 250MA)1414VAC 250W	29
JOHNSON VIKING 500 PLATE DIRECT REPLACEMENT - PLATE TRANS (T-302)	PWDP13046	EI CORE	5	115/230 VAC 60 HZ 1 PH	4800 VCT @ 500 MA CCS	33
JOHNSON VIKING 500 PLATE HIPERSIL REPLACEMENT PLATE TRANS (T-302)		A-0203/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 4800 VCT @ 500 MA CCS	30
JOHNSON VIKING 500 PLATE FWB PLATE XFMR (T-302), FOR FULL WAVE BRIDGE		A-274 C-CORE	10	115/230 VAC 60 HZ 1PH	S1) 0-2000-2350-2800 VAC @ 0.5A CCS	37
JOHNSON VIKING 500 T-301 LV POWER TRANSFORMER, P/N 22.1266	PWDP13025	EI-175 X 1.75	5	115 VAC 60 HZ 1 PH	S1) 960 VCT @ 200MA CCS S2) 560 VCT @ 100MA CCS S3) 6.4 VCT @ 9A CCS S4) 2.5 VCT @ 10A CCS (10 KVDC INSULATION) S5) 5.0 VCT @ 3A CCS	12
JOHNSON VIKING 500 T102 AUDIO DRIVER 4W 6B4 TO PP 6146'S		EI-75 X 1	1	76 VAC @ .050A (170 OHMS DC)	76 VCT @ .050A (180 OHMS DC)	1
JOHNSON VIKING 500-X PLATE OUTBOARD PLATE XFMR (2500 VDC @ 0.8A DC)		A-480 C-CORE	10	115/230 VAC 60 HZ 1PH	5800 VCT @ 0.8A CCS	46
JOHNSON 6N2 T-BOLT FILAMENT FILAMENT TRANSFORMER, T-102		EI-125 X 1.75	5	115 VAC 60 HZ 1 PH	S1) 2.5 VAC @ 10A CCS S2) 6.0 VAC @ 6A CCS S3) 115 VAC @ 0.1A CCS	6
JOHNSON 6N2 T-BOLT PLATE T101 PLATE TRANSFORMER		EI-212 X 4	2	115/230 VAC 60 HZ 1 PH	S1) 4800 VCT @ 0.5A CCS	38
LOUDENBOOMER MK 2 PLATE TRANSFORMER		A-0393/ C-CORE	10	115/230 VAC 60 Hz	S1) 6570 VCT @ 300 MA CCS FWCT CHK INPUT	23
MCABEE A-518-10 MULTI-SEC-#1 PLATE/SCREEN/BIAS/FILAMENT TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-1600-2000 VAC @ 2.0A CCS S2) 6.0 VAC @ 21A CCS (8 EA 4CX250R'S) S3) 280 VCT @ 0.25A CCS S4) 90 VAC @ 0.1A CCS	66
MFJ P/N 406-1418-X SPECIAL HEAVY DUTY MODEL FOR AL-1500		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1PH	S1) 2570 VAC @ 1.0A CCS	46
MFJ P/N 406-1418-1DX EXTRA HEAVY DUTY AL-1500 TRANSFORMER		A-0516/ C-CORE	10	0-120 & 0-100-120 VAC 60 HZ 1PH	2800 VAC @ 1.5A ICAS	58
MFJ P/N 406-1418-1DX-J EXTRA HD AL-1500 XFMR, 100/200 VAC PRI		A-0516/ C-CORE	10	100/200 VAC 50/60 HZ 1PH	2800 VAC @ 1.5A ICAS	58
MFJ P/N 406-1418-1J "J" IS JAPANESE VERSION FOR AL-1200		A-274/C C-CORE	10	100/200 VAC 50/60 HZ	2570 VAC @ 800MA ICAS	37
MOD TRANSFORMER 1200 WATT PP 304TL'S @ 12,000 OHMS P-P		A-550/C C-CORE	9	2872 VCT @ 0.34A CCS (12,000 OHMS P-P)	1768 VAC @ 0.39A CCS (2500 VDC @ .55A)	137
MOD TRANSFORMER 30 WATT SINGLE 807 @ 450 VDC @ 150MA DC THRU SEC		EI-175 X 1.75 29G M6	4	16.4 VAC @ 2.0A CCS (8 OHMS)	S1) 318 VAC @ 0.106A CCS (3000 OHMS)	12

Description	Hammond Part Number	Core	Style (see above)	Approx. Weight (lbs)		
				Primary	Secondary	
MOD TRANSFORMER 300 WATT PP 4CX150A'S @ 17600 OHMS P-P		A-0518/ C-CORE	9	2100 VCT @ 0.17A CCS (17,600 OHMS P-P)	1414 VAC @ 0.18A CCS (2000 VDC @ .25A)	38
MOD TRANSFORMER 500 WATT PP 813'S TO SINGLE 813 @ 2000 VDC @ .25A		A-0525/ C-CORE	9	1768 VCT @ 0.2A CCS (PP 813'S 16K PP)	1414 VAC @ 0.25A DC (2000 VDC @ 0.25A)	49
NATIONAL HRO-60 FILTER CHOKE WITH ADAPTER PLATE FOR SAME MOUNTING		EI-100 X 1.5	5	17 HY @ 0.1A DC (410 OHMS DCR)		3
NATIONAL HRO-60 POWER (R) NOT EXACT REPLACEMENT BUT WILL FIT IN	PWDP13224	EI-150 X 2	5	115/230 VAC 60 HZ 1 PH	S1) 550 VCT @ 200 MA CCS S2) 5.0 VAC @ 3A CCS S3) 0-6.3-13.3 VAC @ 6A CCS	10
NATIONAL NC-183 POWER	PWDP13122	EI	6	115/230 VAC 60 HZ 1 PH		8
NATIONAL NCL-2000 FIL/BIAS T2 (FILAMENT & BIAS), P/N C51440		EI-087 X 2.250	5	115 VAC 60 HZ 1 PH	S1) 130 VCT @ 50 MA CCS S2) 13.5 VAC @ 3A CCS	2
NATIONAL NCL-2000 POWER TRANSFORMER (PLATE & SCREEN) VOLTAGES	PWDP13091	EI-175 X 4	2	117/234 VAC HI-LO TAPS 60 HZ 1PH	S1) 1080 VRMS @ 0.91 AMPS CCS S2) 450 VRMS @ 0.070 AMPS CCS	25
NATIONAL NCX-1000 POWER PLATE, DRIVER PLATE & SCREEN VOLTAGES	PWDP13003	EI-175 X 2.5	2	117/234 VAC 60 HZ 1 PH	S1) 1100 VAC @ 0.36A CCS S2) 0-240-480 VAC @ 0.20A CCS	17
PALOMAR 300A POWER	PWDP13148	EI-150 X 2 1/2"	5	117 VAC 60 HZ 1 PH	S1) 310 VRMS @ 1.0 AMP CCS S2) 14 VRMS @ 8 AMPS CCS	
PITTENGER JP1815 FOR AMP IN AUG 84 ISSUE OF HAM RADIO		A-480 C-CORE	10	240 VAC 60 HZ 1 PH	1800 VRMS @ 1.5A CCS	46
PITTENGER JP1815 W/18V @ 1A FOR AMP IN AUG 84 ISSUE OF HAM RADIO		A-480 C-CORE	10	240 VAC 60 HZ 1 PH	S1) 1800 VRMS @ 1.5A CCS S2) 18 VRMS @ 1.0A CCS	46
PITTENGER P/N FT-800A7 DUAL 3CX800A7 FILAMENT TRANSFORMER		EI-100 X 1	1	120 VAC 60 HZ 1 PH	13.5 VAC @ 3.0A CCS	2
PITTENGER P/N JP3315 PLATE FOR J. PITTENGER 8877 AMP IN SEPT 86 QST	PWDP13166	A-0518/ C-CORE	10	230 VAC 60 HZ 1 PH	0-2300-2600-3300 VAC @ 1.5A CCS	66
PITTENGER P/N PT-2475 FOR K8RA AMPS DESCRIBED IN ARRL HANDBOOK	PWDP13239	A-0518/ C-CORE	10	117/234 VAC 60 HZ 1 PH	0-1770-2125-2475 VAC @ 1.5A CCS	66
PITTENGER P/N PT-2475-01 ADDITIONAL SEC TAP @ 1414 VAC		A-0518/ C-CORE	10	117/234 VAC 60 HZ 1 PH	0-1414-1770-2125-2475 VAC @ 1.5A CCS	66
PITTENGER P/N PT-2475-1 1.35 AMP CCS VERSION OF PT-2475		A-0516/ C-CORE	10	117/234 VAC 60 HZ 1 PH	0-1770-2125-2475 VAC @ 1.35A CCS	58
PRIME INST P/N AL-80A-MB SPECIAL DESIGN		EI-162 X 3	4	120/240 VAC 60 HZ 1 PH	S1) 2100 VAC @ 0.3A CCS S2) 5.5 VCT @ 15A CCS S3) 10 VAC @ 2.0A CCS	21
PRIME INST P/N AL1800T PLATE TRANSFORMER		A-393 C-CORE	10	117/234 VAC 60 HZ 1PH	0-1200-1650-1800 VAC @ 500 MA CCS	23
PRIME INST P/N AL2080		A-274 C-CORE	10	120/240 VAC 60 HZ 1PH	2080 VAC @ 0.8A ICAS	37
PRIME INST P/N AL2080A		A-393 C-CORE	10	120/240 VAC 60 HZ 1PH	2080 VAC @ 0.5A CCS	23
PRIME INST P/N AL2400 PLATE TRANSFORMER		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 0-1700-2400 VAC @ 500 MA CCS	23

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
PRIME INST P/N AL8A		EI-162 X 3.5	4	117/234 VAC 60 HZ 1 PH	S1) 970 VAC @ 700 MA CCS S2) 5.0 VCT @ 15A CCS S3) 12 VAC @ 2A CCS	24
PRIME INST P/N AL84T		A-0016/ C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-600-850 VAC @ 1.0A ICAS S2) 6.0 VAC @ 8A CCS	17
PRIME INST P/N AL88T		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1PH	S1) 0-1700-2400 VAC @ 0.5A S2) 10 VAC @ 2.0A S3) 5 VAC @ 10A	23
PRIME INST P/N AR-418		A-0274/ C-CORE	10	120/240 VAC 50/60 HZ 1 PH	S1) 2570 VAC @ 800MA	37
PRIME INST P/N AR-418-M PLATE TRANSFORMER		A-274 C-CORE	10	0-220-240 VAC 50/60 HZ 1 PH	S1) 2872 VAC @ 800 MA ICAS	37
PRIME INST P/N AR418-1J "J" IS JAPANESE VERSION		A-274/C C-CORE	10	100/200 VAC 50/60 HZ	S1) 2570 VAC @ 800MA ICAS	37
RADIO INDUSTRIES MK II CH1 SWINGING CHOKE		EI-150 X 2.5" 29GM6X	2	16 HY @ 50MA TO 4 HY @ 350MA		12
REL MODEL L-103 FILTER CHOKE PR 4CX300AS @ 2500 VDC @ 500 MA		EI-175 X 3	4	25 HY @ 50MA TO 5 HY @ 500MA DC		19
SIGNAL ONE CX7A		A-0371/ C-CORE	9	117/234 VAC 60 HZ 1 PH	S1) 230 VAC @ 0.1A CCS S2) 43 VCT @ 1.0A CCS S3) 575 VAC @ 0.2A CCS	8
SIGNAL ONE 1030 MILSPEC 1030 TRANSCEIVER POWER XFMR		A-0371/ C-CORE	9	120/240 VAC 60 HZ 1 PH	S1) 22.0 VAC @ 20 AMPS	8
SPC 15.0 VCT @ 15A CCS D 3CX10000B7 FILAMENT TRANSFORMER		EI-175 X 1.75	2	120 VAC 60 HZ 1 PH	S1) 15.0 VCT @ 15A CCS	12
STANCOR P-8339		EI-150 X 2.5	5	117 VAC 60 HZ 1 PH	S1) 650 VCT @ 300 MA CCS S2) 5.0 VAC @ 3A CCS S3) 12.6 VCT @ 5.25A CCS	12
STANCOR P-8339-1		EI-150 X 2.5	5	117 VAC 60 HZ 1 PH	S1) 600 VCT @ 300 MA CCS S2) 12.6 VCT @ 5.25A CCS	12
STANCOR P/N P-8031 HIPERSIL VERSION OF STANCOR P/N P-8031		A-518/C C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 2075-1775-0-1775-2075 VAC @ 0.5A CCS	66
STANCOR P/N PC-8417 30 VA LV RECTIFIER POWER TRANSFORMER		EI-100 X 1	5	0-110-115 VAC 60 HZ 1 PH	S1) 440 VCT @ 0.050A CCS S2) 6.3 VAC @ 0.6A CCS S3) 25.2 VAC @ 0.5A CCS	2
SVETLANA 4CX800A FIL XFMR FIL & BIAS XFMR FOR 2 TUBES		EI-150 X 1.5	4	0-115-120-125 VAC 60 HZ 1 PH	S1) 12.6 VAC @ 8A CCS S2) 150 VAC @ 0.1A CCS	8
SVETLANA 4CX800A FIL, BIAS, SCREEN XFMR FIL & BIAS XFMR FOR 2 TUBES WITH HIGHER SCREEN VOLTAGE	PWDP13193	EI-150 X 1.5	4	0-115-120-125 VAC 60 HZ 1 PH	S1) 12.6 VAC @ 8A CCS S2) 70 VAC @ 150 MA CCS S3) 250 VAC @ 0.25A CCS	8
SVETLANA 4CX800A PLATE XFMR 2500 VDC @ 1.0A ICAS FROM FWC CAP INPUT		A-0274/ C-CORE	10	0-230-240-250 VAC 60 HZ 1 PH	S1) 1770 VAC @ 1.5A ICAS	37

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
SWAN MARK I POWER POWER TRANSFORMER FOR SWAN MARK I LINEAR	PWDP13012	EI-162 X 3" 29GAM6X	6	120/240 VAC 60 HZ 1 PH	S1) 0-568-1065 VAC @ 0.5A CCS S2) 10.0 VCT @ 15A CCS S3) 12 VAC @ 1A CCS	21
SWAN MARK VI OUTBOARD POWER		A-480 C-CORE	10	120/240 VAC 60 HZ 1PH	S1) 0-500-1000 VAC @ 2.0A CCS S2) 10.0 VCT @ 15A CCS S3) 12.0 VAC @ 2A CCS	46
SWAN MK II POWER HD SN 10 SM (REQUIRES PS REWORK TO FIT)		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-583-1123 VAC @ 0.8A CCS S2) 10 VCT @ 15A CCS S3) 12.6 VAC @ 2A CCS	23
SWAN MK II POWER HD - HIGHER PLATE VOLTAGE (REQUIRES PS REWORK TO FIT)	PWDP13095	A-0393/ C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-583-1200 VAC @ 0.8A CCS S2) 10 VCT @ 15A CCS S3) 12.6 VAC @ 2A CCS	23
SWAN MK II 3 TUBE OUTBOARD MUST RUN FILAMENTS IN SERIES		A-274 C-CORE	10	117/234 VAC 60 HZ	S1) 588/1123 VAC @ 1.2A CCS S2) 15 VCT @ 15A CCS S3) 12.6 VAC @ 2A CCS	37
SWAN MK II-1 POWER HD SN 10 SM (REQUIRES PS REWORK TO FIT)		A-0393/ C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-583-1300 VAC @ 0.8A CCS S2) 10 VCT @ 15A CCS S3) 12.6 VAC @ 2A CCS	23
SWAN MK-I-X OUTBOARD POWER TRANSFORMER		A-480 C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-568-1065 VAC @ 1.5A CCS S2) 10.0 VCT @ 30A CCS S3) 12 VAC @ 1A CCS	46
SWAN MK-I-X2 HEAVY DUTY OUTBOARD POWER TRANSFORMER		A-0518/ C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 0-568-1065 VAC @ 3.0A CCS S2) 10.0 VCT @ 30A CCS S3) 12 VAC @ 1A CCS	66
SWAN 117-B/C FILTER CHOKE P/N 274-001, 3946524 (2 EA SWAN 400 PS)		EI-62 X .75	1	3.5 HY @ 80 MA DC (+275 VDC SUPPLY)		1
SWAN 117-B/C POWER FOR SWAN 400 AC POWER SUPPLY		EI-150 X 2	6	117 VAC 60 HZ 1 PH	S1) 0-320-640 VAC @ 360 MA CCS S2) 90 VAC @ 140 MA CCS S3) 12.6 VAC @ 3.69A CCS	10
SWAN 117-XC POWER FOR SWAN 350 AC POWER SUPPLY	PWDP13023	EI-150 X 2	4	117 VAC 60 HZ 1 PH (AC PRIMARY)	S1) 0-9.6-14.4-19.2 VAC @ 6A CCS (DC PRI) S2) 427 VAC @ 300 MA CCS S3) 230 VAC @ 300 MA CCS S4) 90 VAC @ 140 MA CCS	10
SWAN 230-XC POWER FOR SWAN 350 AC POWER SUPPLY	PWDP13027	EI-150 X 2" 29G M-6	4	117/234 VAC 50/60 HZ 1 PH (AC PRIMARY)	S1) 0-9.6-14.4-19.2 VAC @ 6A CCS (DC PRI) S2) 427 VAC @ 300 MA CCS S3) 230 VAC @ 300 MA CCS S4) 90 VAC @ 140 MA CCS	10

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
TEN-TEC 422 & 422B - HV TRANSFORMER FOR TEN-TEC MODEL 422 CENTURION LINEAR AMPLIFIER Page 3-1 of the Ten-Tec Centurion Manual (Section 3-1.4) is incorrect. The stock unit was not a 2.5KVA unit nor did it weigh 35 lbs (it weighs 23 lbs.) Special thanks to Steve - KD8ZBG for reporting this.	PWDP13045	B-0393/ C-CORE	10	115/230 VAC 60 HZ 1 P	2225 VAC @ 0.5A CCS	23
TEN-TEC 425 TITAN POWER XFMR T1, MAIN POWER TRANSFORMER	PWDP13039	A-0480/ C-CORE	10	120/240 VAC 50/60 HZ 1 PH	S1) 1270 VAC @ 1.0A CCS S2) 570 VAC @ 1.0A CCS S3) 13.5 VAC @ 6A CCS S4) 20 VAC @ 6A CCS S5) 20 VAC @ 2A CCS	46
TEN-TEC 425 TITAN POWER XFMR-1 HIGHER DC VOLTAGE & 60 HZ ONLY PRIMARY		A-0480/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 1800 VAC @ 1.2A ICAS S2) 600 VAC @ 1.2A ICAS S3) 13.5 VAC @ 6A CCS S4) 20 VAC @ 6A CCS S5) 20 VAC @ 2A CCS	=46
THOMAS LV POWER #01 LOW VOLTAGE POWER TRANSFORMER		EI-150 X 1.5	4	120/240 VAC 60 HZ 1 PH	S1) 290 VCT @ 0.3A CCS S2) 60 VAC @ 0.3A CCS S3) 6.3 VCT @ 10A CCS	8
THORDARSON P/N T-11M77 125-300 WATT MULTI-MATCH MODULATION XFMR		EI	5	PP 811A'S @ 1000 VDC	SINGLE 813 @ 2000 VDC @ 225 MA DC	26
THORDARSON P/N T-21P93		EI-150 X 2.5" 29GM6X	5	117 VAC 60 HZ 1 PH	S1) 2150/1000 VCT @ 95/125 MA CCS FWCT	12
TIBBETTS LV POWER #01 (3) 4CX800A FIL/BIAS/SCREEN XFMR		EI-150 X 1.5" 29GAM6	4	120/240 VAC 60 HZ 1 PH	S1) 12.6 VCT @ 10.8A CCS S2) 270 VCT @ .025A CCS S3) 570 VCT @ .080A CCS	8
TOKYO HY POWER LABS HL-1K T1, (NEED MTG BRKTS FROM OLD XFMR)		EI-175 X 3" 29G M6X	2	0-100-110-117/0-100-110-117 VAC 60 HZ	S1) 850 VAC @ 0.5A CCS S2) 280 VAC @ 0.1A CCS S3) 100 VAC @ 0.1A CCS S4) 12 VAC @ 3A CCS	19
TRANSWORLD P/N 410012 T9, T10, T11 OR T12 IN TRANSWORLD SS AMP	PWDP13167	EI-125 X 1.25" 29GM6	2	120 VAC 60 HZ 1 PH	15.1 VAC @ 8A CCS	4
TRIAD P-11A WILL YIELD 600 VDC @ 250 MA FROM FWCT		EI-150 X 2	5	115 VAC 60 Hz	S1) 1455 VCT @ 250 MA CCS	10
TRIAD P-216AL PLATE TRANSFORMER (WITHOUT END COVERS)		EI-212 X 3	4	115/230 VAC 60 HZ 1PH	S1) 2430 VCT @ 500 MA CCS (FWCT)	29
TRIAD P-217AL PLATE TRANSFORMER	PWDP13040	EI-175 X 2.5" 29GAM6	5	115/230 VAC 50/60 HZ 1 PH	2880 VCT @ 0.25A DC (FWCT)	17
TRIAD P-3A POWER TRANSFORMER		EI-175 X 1.75	5	115 VAC 60 HZ 1 PH	S1) 600/300 VCT @ 0.3A CCS S2) 5.0 VAC @ 4A CCS	12
TRIAD P-9A POWER TRANSFORMER		EI-175 X 3"	5	115 VAC 60 HZ 1 PH	S1) 1236 VCT @ 500 MA CCS (FWCT) S2) 5 VAC @ 6A CCS	19

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
TRIAD P/N 70581 HENRY 2K-4 REPLACEMENT POWER TRANSFORMER	EI-250 X 3.125		4	115/230 VAC 60 HZ 1 PH	S1) 3500 VAC @ 0.4A CCS S2) 10.2 VCT @ 15A CCS	42
TRIAD R-14A POWER XFMR PLATE & FILAMENT TRANSFORMER	EI-I25 X 1.5		5	115 VAC 60 HZ 1 PH	S1) 700 VCT @ 125 MA CCS S2) 5.0 VAC @ 3A CCS S3) 6.3 VCT @ 4.5A CCS	5
TRIAD R-83A O-12 OSCILLOSCOPE POWER TRANSFORMER	EI-II2 X 1.875		5	115 VAC 60 HZ 1 PH	S1) 800 VCT @ 70 MA DC CCS S2) 650 VAC @ 3 MA DC CCS S3) 1.25 VAC @ 0.3A CCS S4) 6.3 VCT @ 3.5A CCS S5) 6.3 VAC @ 0.6A CCS	5
UTC CVM-2 60W MULTI-MATCH MOD XFMR IN RC-150 CASE	EI		5	18K-2K OHMS P-P CENTER TAPPED	S1) 30K-200 OHMS RF PA (60 WATTS AUDIO OUT)	11
VECTRONICS HF600-QSK POWER SINGLE 3-500Z IN GROUNDED GRID	EI-200RX 2" 29GAM6X		4	0-120 & 0-80-100-120 VAC 60 HZ 1 PH	S1) 1240 VAC @ 0.4A CCS S2) 21 VAC @ 0.2A CCS S3) 5.8 VCT @ 15A CCS	18
VR GLOBE KING 500 MOD XFMR PP 811A'S TO SINGLE 4-250A/4-400A RF PA	EI-150 X 3.5" 29GM6X		5	1465 VCT @ 0.246A CCS (7400 OHMS P-P)	S1) 1275 VAC @ 0.283A CCS (1800 VDC @ .4A)	16
YAESU FL-2000B LV PWR T2 FILAMENT & CONTROL VOLTAGE TRANSFORMER	EI-112 X 1.5" 29GAM6		2	0-100-110-117 & 0-100- 110-117 VAC 60 HZ	S1) 6.5 VCT @ 8A CCS S2) 13 VAC @ 1A CCS	4
YAESU FL-2100B POWER XFMR P/N 21002, T1, FOR PAIR OF 572B'S	EI-175 X 3" 29GAM6X		6	0-100-110-117 & 0-100- 110-117 VAC 60 HZ	S1) 0-425-620-850 VAC @ 1A ICAS S2) 6.5 VCT @ 8A CCS S3) 13 VAC @ 1A CCS	19
YAESU FT-901 POWER XFMR WITHOUT DC WINDINGS & DUAL PRIMARY	EI-137 X 2.5		6	0-100-110-117 VAC 60 HZ 1 PH	S1) 320 VCT @ 0.5A CCS S2) 0-120-190-250 VAC @ 0.1A CCS S3) 11.5-0-11.5-12.6 VAC @ 2A CCS	10
YAESU TEMPO AC ONE PWR XFMR TEMPO AC ONE POWER SUPPLY WITH SPEAKER	EI-150 X 2.5" 29GM6X		6	0-100-110-117 & 0-100- 110-117 VAC 60 HZ	S1) 0-240-460-600 VAC @ 0.275A CCS S2) 270 VCT @ 0.2A CCS S3) 100 VAC @ 0.1A CCS S4) 6.3 VAC @ 6A & 6.3 VAC @ 6A	12
7.5VCT @ 75A FILAMENT	PWDF13207			0-220-240VAC, 60HZ	7.5 VCT @ 75A CCS	
7.5VCT @ 100A FILAMENT	PWDF13185			115/230 VAC, 50/60 HZ	7.5VCT @ 100A CCS	
10.0 VCT @ 10A DUAL CCS G DUAL 10 VCT 10A FIL FOR PP 833A'S	EI-150 X 2		5	115/230 VAC 60 HZ 1PH	S1) 10.0 VCT @ 10A CCS S2) 10.0 VCT @ 10A CCS	10
10.0 VCT @ 10A E FIL XFMR FOR 810'S, 813'S OR SINGLE 833A	EI-150 X 1.5		2	0-105-117 VAC 60 Hz 1 PH	S1) 10.0 VCT @ 10A CCS S2) 10.0 VCT @ 10A CCS	8
10.0 VCT @ 15A CCS R 11.8 VAC 180-1000 HZ PRIMARY	EI-125 X 1.25" 29GM6		2	11.8 VAC 180-1000 HZ 1 PH	S1) 10.0 VCT @ 15A CCS	4

Description	Hammond Part Number	Core	Style (see above)	Primary		Secondary		Approx. Weight (lbs)
10.0 VCT @ 17.5A 3CX5000A FILAMENT TRANSFORMER		EI-150 X 2	5	115/230 VAC 60 HZ 1PH		S1) 10.0 VCT @ 17.5A CCS		10
10.0 VCT @ 20A CCS G FILAMENT TRANSFORMER		EI-150 X 2	5	115/230 VAC 60 HZ 1PH		S1) 10.0 VCT @ 20A CCS		10
10.5 VCT @ 140A CCS M FILAMENT TRANSFORMER, 4CX20000A/8990		A-0274/ C- CORE	10	0-208-220-230-240-250 VAC 60 HZ 1 PH		S1) 10.5 VCT @ 140A CCS		37
1000 VAC @ 1.0A CCS PLATE TRANSFORMER		A-0393/ C- CORE	10	115 VAC 60 HZ 1 PH		S1) 1000 VAC @ 1.0A CCS		23
1000 VAC @ 1.75A CCS K PLATE TRANSFORMER		A-274 C- CORE	10	230 VAC 60 HZ 1 PH		1000 VAC @ 1.75A CCS		37
1100 VAC @ 1.2A CCS I ADVERTISED UNIT		A-274 C- CORE	10	120/240 VAC 60 Hz		S1) 1100 VAC @ 1.2A CCS		37
1100 VAC @ 1.5A CCS I PLATE TRANSFORMER		A-274 C- CORE	10	120/240 VAC 60 HZ 1 PH		1100 VAC @ 1.5A CCS		37
1100 VAC @ 2.8A ICAS I ADVERTISED UNIT		A-0459/ C- CORE	10	120/240 VAC 60 HZ 1 PH		S1) 1100 VAC @ 2.8A ICAS		40
1100 VAC @ 600 MA CCS H BERKSHIRE P/N 6181		A-0016/ C- CORE	10	117/234 VAC 60 HZ 1 PH		S1) 1100 VAC @ 600 MA CC		17
1171 VAC @ 1.0A CCS G PLATE TRANSFORMER		B-0393/ C- CORE	10	115/230 VAC 60 HZ 1 PH		S1) 1171 VAC @ 1.0A CCS		23
1175 VAC @ 3.5A CCS N PLATE TRANSFORMER		A-0518/ C- CORE	10	0-220-240 VAC 60 HZ 1 PH		S1) 1175 VAC @ 3.5A CCS		66
1200 VAC @ 0.5A CCS & FIL WITH 6.3 VCT @ 16A FILAMENT WINDING		A-393 C- CORE	10	115 VAC 60 HZ 1 PH		S1) 1200 VAC @ 0.5A CCS S2) 6.3 VCT @ 16A CCS		23
1250 VAC @ 1.5A CCS G PLATE TRANSFORMER		A-0480/ C- CORE	10	115/230 VAC 60 HZ		S1) 1250 VAC @ 1.5A CCS		46
13.5 VCT @ 3A CCS N FILAMENT TRANSFORMER		EI-125 X 1.25	4	0-220-240 VAC 60 HZ 1 PH		S1) 13.5 VCT @ 3A CCS		4
13.5 VCT @ 5A & 18 VAC @ 2A 3CX800A7 FIL & CONTROL XFMR (3 TUBES)		EI-137 X 1.375	5	0-210-220-230-240-250 VAC 60 HZ 1 PH		S1) 13.5 VAC @ 5A CCS S2) 18 VAC @ 2A CCS		6
13.5 VCT @ 5A G 3CX800A7 FILAMENT TRANSFORMER (3 TUBES)		EI-137 X 1.375	4	115/230 VAC 60 HZ 1 PH		S1) 13.5 VCT @ 5A CCS		6
1300/1175/1050/925V @ 2A CCS 1296 MHZ EME AMP POWER SUPPLY XFMR		A-0480/ C- CORE	10	34 VAC 60 HZ 1 PH		S1) 0-925-1050-1175- 1300 VAC @ 2.0A CCS		46
14 VAC @ 100A CCS F LV POWER TRANSFORMER		A-0203/ C- CORE	10	110/220 VAC 60 HZ 1 PH		S1) 14 VAC @ 100A CCS		30
15 VAC @ 25A CCS OR 35A ICAS FOR 13.8 VDC REGULATED POWER SUPPLY		EI-162 X 2	2	115 VAC 60 HZ 1 PH		S1) 15 VAC @ 25A CCS OR 35A ICAS		15
15.0 VCT @ 15A CCS D 3CX10000B7 FILAMENT TRANSFORMER		EI-175 X 1.75	2	120 VAC 60 HZ 1 PH		S1) 15.0 VCT @ 15A CCS		12
15.0 VCT @ 15A CCS SP LO-PRO LO-PROFILE FILAMENT TRANSFORMER		EI-150 X 2" 29GAM6X	4	0-115-120-125-130 VAC 60 HZ 1 PH		S1) 15.0 VCT @ 15A CCS		10
1500 VAC @ 0.5A & 7 VCT @ 8A POWER XFMR FOR DUAL 572B LINEAR AMP		A-393 C- CORE	10	120 VAC 60 HZ 1 PH		S1) 1500 VAC @ 0.5A CCS S2) 7.0 VCT @ 8A CCS		23
1500 VAC @ 0.5A CCS & S/B/F W/FIL, SCREEN & BIAS VOLTAGE SECONDARIES		A-0393/ C- CORE	10	120/240 VAC 60 HZ 1 PH		S1) 1500 VAC @ 0.5A CCS S2) 300 VAC @ 0.1A CCS S3) 100 VAC @ 0.1A CCS S4) 6.3 VAC @ 6A CCS		23
1500 VAC @ 1.0A CCS PLATE TRANSFORMER		A-0274/ C- CORE	10	0-220-240 VAC 60 HZ 1 PH		S1) 1500 VAC @ 1.0A CCS		37
1500 VAC @ 1.0A CCS PLATE TRANSFORMER	PWDP13100	EI	4	0-220-240 VAC 60 HZ 1 PH		S1) 1500 VAC @ 1.0A CCS		45
1600 VAC @ 0.5A CCS H PLATE TRANSFORMER		A-0393/ C- CORE	10	117/234 VAC 60 HZ 1 PH		S1) 1600 VAC @ 0.5A CCS		23

Description	Hammond Part Number	Core	Style (see above)	Approx. Weight (lbs)	
				Primary	Secondary
1600 VAC @ 1.5A CCS N PLATE TRANSFORMER		A-480 C-CORE	10	0-220-240 VAC 60 HZ	S1) 0-1600 VAC @ 1.5A CCS 46
1650/1515/1375V @ 1.2A CCS K FOR 2000 VOLT SUPPLY IN ARRL HANDBOOK	PWDP13078	A-0480/ C-CORE	10	234 VAC 60 HZ 1 PH	0-1375-1515-1650 VAC @ 1.2A CCS 46
1770 VAC @ 2.0A CCS PLATE TRANSFORMER		A-0518/ C-CORE	10	0-230-240-250 VAC 60 HZ 1 PH	S1) 1770 VAC @ 2.0A CCS 66
18 VAC @ 25A CCS OR 35A ICAS FOR 13.8 VDC REGULATED POWER SUPPLY		EI-162 X 2	2	115 VAC 60 HZ 1 PH	S1) 18 VAC @ 25A CCS OR 35A ICAS 15
18/16 VAC @ 100A CCS A LV POWER XFMR WITH HI/LO PRIMARY TAPS		A-0274/ C-CORE	10	110 VAC 60 HZ 1 PH	0-16-18 VAC @ 100A CC 37
1800 VAC & 1.5A CCS LV & FIL PLATE XFMR WITH LV & FILAMENT WINDINGS		A-0518/ C-CORE	10	240 VAC 60 HZ 1 PH	S1) 1800 VAC @ 1.5A CCS S2) 500 VCT @ 0.1A CCS S3) 6.3 VCT @ 12A CCS 66
1800 VAC @ 0.6A & 5 VCT @15A PLATE & FIL XFMR TRANSFORMER		A-0274/ C-CORE	10	117 VAC 60 HZ 1 PH	S1) 1800 VAC @ 0.6A CCS S2) 5.0 VCT @ 15A CCS 37
1800 VAC @ 1.5A CCS K PLATE TRANSFORMER		A-0480/ C-CORE	10	230 VAC 60 HZ 1 PH	S1) 1800 VAC @ 1.5A CCS 46
1800 VAC @ 1A CCS G PLATE TRANSFORMER		A-0274/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 1800 VAC @ 1A CCS 37
1800 VAC @ 2A CCS KN PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-230-240 VAC 60 HZ 1 PH	1800 VAC @ 2A CCS 66
1800 VCT @ 3A CCS		A-525 C-CORE	10	0-115 & 0-115 VAC 60 HZ	0-900-1800 VCT @ 3.0A CCS 86
1800/1200 VAC @ 0.5A CCS PLATE TRANSFORMER		A-0393/ C-CORE	10	120 VAC 60 HZ 1 PH	0-1200-1800 VAC @ 0.5A CCS 23
1800/1600/1500V @ 1.5A CCS N PLATE TRANSFORMER WITH 2 SEC TAPS		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-1500-1600-1800 VAC @ 1.5A CCS 46
1800VCT @ 175 MA	PWDP13048	EI CORE		120VAC, 60 HZ	S1)1800VAC @ 175 MA S2) 560 VAC @ 800 MA S3) 5V @ 2A S4) 5V @ 4A
19/18/17/16/15 VAC @ 30A CCS WITH 115 VAC VCB PRIMARY TAPS		A-16 C-CORE	10	115 VAC 60 HZ WITH 4 CB TAPS	S1) 19/18/17/16/15 VAC @ 30A CCS 17
2.5 VCT @ 10A B (15 KV INS) PR 866A RECTIFIER FILAMENT TRANSFORMER		EI-150 X 1.5	5	115 VAC 60 HZ 1 PH	2.5 VCT @ 10A CCS (15 KVDC TEST) 8
2000 VAC @ 0.5A CCS N PLATE TRANSFORMER		A-0274/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	2000 VAC @ 0.5A CCS 37
2000 VAC @ 1.0A CCS I PLATE TRANSFORMER		A-0480/ C-CORE	10	120/240 VAC 60 HZ 1 PH	2000 VAC @ 1.0A CCS 46
2000 VAC @ 1.0A CCS N PLATE TRANSFORMER		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 2000 VAC @ 1.0A CCS 46
2000 VAC @ 1.0A ICAS J 3CX800A7 PLATE TRANSFORMER		A-0274/ C-CORE	10	220 VAC 60 HZ 1 PH	2000 VAC @ 1.0A CCS 37
2000 VAC @ 1.5 AMP CCS		A-0480/ C-CORE	10	230 VAC 60 HZ 1PH	2000 VAC @ 1.5 AMP CCS 46
2000 VAC @ 2A CCS N PLATE TRANSFORMER		A-518 C-CORE	10	220/240 VAC 60 HZ 1 PH	S1) 2000 VAC @ 2.0A CCS 66
2000 VAC @ 2.5A CCS PLATE TRANSFORMER	PWDP13059	EI CORE	2	240 VAC 60 HZ 1 PH	2000 VAC @ 2.5A CCS 84
2000 VAC @ 3.0A CCS N PLATE TRANSFORMER		A-525 C-CORE	10	0-220-240 VAC 60 HZ 1 PH	2000 VAC @ 3.0A CCS 86
2000 VAC @ 500 MA CCS G HIGH VOLTAGE TRANSFORMER		A-0393/ C-CORE	10	115/230 VAC 60 HZ 1 PH	2000 VAC @ 500 MA CCS 23
2000 VCT @ 0.5A CCS L PLATE TRANSFORMER FOR FWB		A-0274/ C-CORE	10	240 VAC 60 HZ 1 PH	2000 VCT @ 0.5A CCS 37

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
2000/1300 VAC @ 3.0A CCS N PLATE TRANSFORMER WITH SEC TAP		A-0525/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	0-1300-2000 VAC @ 3.0A CCS	86
2250/2000/1500 VAC @ 1A CCS PLATE TRANSFORMER		A-480 C-CORE	10	0-220-240 VAC 60 HZ 1 PH	0-1500-2000-2250 VAC @ 1.0A CCS	46
2300 VCT @ 0.55A CCS D PLATE TRANSFORMER		A-274 C-CORE	10	120 VAC 60 HZ 1 PH	2300 VCT @ 550 MA CCS	37
2300 VCT @ 2.0A CCS PLATE TRANSFORMER	PWDP13190	EI	2	220 VAC 60 HZ 1 PH	2300 VCT @ 2.0A CCS	85
2350/1800/1700 VAC @ 1.0A CS PLATE TRANSFORMER		A-0480/ C-CORE	10	0-230-240-250 VAC 60 HZ 1 PH	0-1700-1800-2350 VAC @ 1.0A CCS	46
24 VCT @ 25A CCS LOW VOLTAGE POWER TRANSFORMER		A-16 C-CORE	10	115 VAC 60 HZ 1 PH	24 VCT @ 25A CCS	17
2400 VAC @ .4A & 5 VCT @ 15A PLATE & FIL XFMR FOR SINGLE 3-500Z	PWDP13004	EI-162 X 3" 29GAM6X	4	117 VAC 60 HZ 1 PH	S1) 2400 VAC @ 0.4A ICAS S2) 5.0 VCT @ 15A CCS	21
2400 VAC @ 0.5A CCS		A-0393/ C-CORE	10	120/240 VAC 60 HZ 1PH	S1) 2400 VAC @ 0.5A CCS	23
2400 VAC @ 1.0A CCS I PLATE TRANSFORMER	PWDP13209	A-0480/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 2400 VAC C.T. @ 1.0A CCS	46
2400 VAC @ 1.5A CCS & FIL F WITH 5.0 VCT @ 45A CCS FILAMENT WINDING		A-0518/ C-CORE	10	110/220 VAC 60 HZ 1 PH	S1) 2400 VAC @ 1.5A CCS S2) 5.0 VCT @ 45A CCS	66
2400 VAC @ 1.5A ICAS N PLATE XFMR FOR PAIR OF 3-500Z'S W/TB'S		A-0480/ C-CORE	10	0-220-240 VAC @ 60 HZ 1 PH	S1) 2400 VAC @ 1.5A ICAS	46
2400 VAC @ 2.0A CCS N ADVERTISED UNIT		A-0518/ C-CORE	10	0-220-240 VAC 60 Hz	S1) 2400 VAC @ 2.0A CCS	66
2400 VCT @ .5A & 5 VCT @ 15A PLATE & FIL XFMR FOR SINGLE 3-500Z		EI-162 X 3" 29GAM6X	4	117 VAC 60 HZ 1 PH	S1) 2400 VCT @ 0.5A ICAS S2) 5.0 VCT @ 15A CCS	21
2400 VCT @ 0.5A CCS		A-0393/ C-CORE	10	120/240 VAC 60 HZ 1PH	S1) 2400 VCT @ 0.5A CCS	23
2400/1800 VAC @ 1.5A CCS N		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ	S1) 0-1800-2400 VAC @ 1.5A CCS	66
2400/1800 VAC @ 1.5A ICAS G PLATE XFMR FOR PAIR OF 3-500Z'S		A-0480/ C-CORE	10	115/230 VAC @ 60 HZ 1 PH	S1) 0-1800-2400 VAC @ 1.5A ICAS	46
2400/1800 VAC @ 1.5A ICAS N PLATE XFMR FOR PAIR OF 3-500Z'S		A-0480/ C-CORE	10	220/240 VAC @ 60 HZ 1 PH	S1) 0-1800-2400 VAC @ 1.5A ICAS	46
2400/1800 VAC @ 2.0A CCS N		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	0-1800-2400 VAC @ 2.0A CCS	66
2400/2000 VAC @ 3A CCS		A-0525/ C-CORE	10	0-220-240 VAC 60 HZ	0-2000-2400 VAC @ 3.0A CCS	86
2500 VAC @ 0.3A CCS L PLATE TRANSFORMER		A-0393/ C-CORE	10	240 VAC 60 HZ 1 PH	S1) 2500 VAC @ 0.3A CCS	23
2500 VAC @ 0.5A ICAS D PLATE TRANSFORMER		A-0393/ C-CORE	10	120 VAC 60 HZ 1 PH	S1) 2500 VAC @ 500 MA ICAS	23
2500 VAC @ 1.0A CCS D PLATE TRANSFORMER		A-480 C-CORE	10	120 VAC 60 HZ 1 PH	S1) 2500 VAC @ 1.0A CCS	46
2500 VAC @ 1.0A CCS N PLATE TRANSFORMER		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 2500 VAC @ 1.0A CCS	46
2500 VAC @ 1.5A CCS H PLATE TRANSFORMER WITH 117/234 VAC PRI		A-518/C C-CORE	10	117/234 VAC 60 HZ 1 PH	S1) 2500 VAC @ 1.5A CCS	66
2500 VAC @ 1.5A CCS N PLATE TRANSFORMER		A-518/C C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 2500 VAC @ 1.5A CCS	66
2500 VCT @ 1.5A CCS N PLATE TRANSFORMER		A-518/C C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 2500 VAC @ 1.5A CCS	66
2500 VCT @ 2.5A CCS N PLATE TRANSFORMER	PWDP13228			120/240 VAC, 60 HZ	S1) 2500 VAC @ 2.5A CCS	

Description	Hammond Part Number	Core	Style (see above)	Approx. Weight (lbs)	
				Primary	Secondary
2500 VCT @ 400 MA CCS B FOR FWB RECTIFIER		A-0393/ C-CORE	10	115 VAC 60 HZ 1 PH	S1) 2500 VCT @ 400 MA CCS (FWB) 23
2500/1750 VAC @ 0.8A CCS G PLATE TRANSFORMER		A-0274/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-1750-2500 VAC @ 0.8A CCS 37
2600 VAC @ 1.5A CCS N PLATE XFMR FOR 3-4 EA 3-500Z (3250 VDC)		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 2600 VAC @ 1.5A CCS 66
2600/2400/1800 VAC @ 2A CCS PLATE XFMR FOR 4 EA 3-500Z'S		A-0525/ C-CORE	10	0-220-230-240 VAC 60 Hz	0-1800-2400-2600 VAC @ 2A CCS 86
2650/1800 VAC @ 1.5A CCS N PLATE XFMR FOR 3-4 EA 3-500Z (3300 VDC)		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	0-1800-2650 VAC @ 1.5A CCS 66
2800 VCT @ 400 MA CCS PLATE TRANSFORMER		EI-212 X 4	2	120/240 VAC 60 HZ 1 PH	S1) 2800 VCT @ 400 MA CCS 38
2800/2000 VAC @ 1.0A CCS PLATE TRANSFORMER		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 2800 VAC @ 1.0A CCS 46
2800/2700/2600 VAC @ 1.5A ICAS PLATE TRANSFORMER	PWDP13182	EI	2	0-240 VAC 60 HZ 1 PH	0-2600-2700-2800 VAC @ 1.5A ICAS
2800/2400 VAC @ 2.5A CCS N PLATE TRANSFORMER	PWDP13077	A-0525/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-2400-2800 VAC @ 2.5A CCS 86
2850/1750 VAC @ 1.5A ICAS G PLATE TRANSFORMER		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-1750-2850 VAC @ 1.5A ICAS 46
2850/2150/1450V @ 1.5A ICAS SPECIAL FOR Q-PRODUCTS WITH EXTRA TAP		A-0480/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-1450-2150-2850 VAC @ 1.5 AMP ICAS 46
290 VAC @ 0.1A CCS N 400 VDC 100 MA DC SCREEN SUPPLY XFMR		EI-125 X 1.25	4	0-220-240 VAC 60 HZ 1 PH	S1) 290 VAC @ 0.1A CCS 4
3000 VAC @ 1.0A CCS N PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 3000 VAC @ 1.0A CCS 66
3000 VAC @ 1.5A CCS HI/LO PRI LO TAP TO PROVIDE 2000 VAC		A-518	10	220 VAC 60 HZ WITH HI/LO TAPS	3000/2000 VAC @ 1.5 AMP CCS 66
3000 VAC @ 2 AMP CCS WITH 2650 VAC TAP & 220-230-240-250V PRI		A-0525/ C-CORE	10	0-220-230-240-250 VAC 60 HZ	S1) 0-2650-3000 VAC @ 2 AMPS CCS OR 3A ICAS 86
3000 VAC @ 3 AMP CCS N		A-0530/ C-CORE	10	220/240 VAC 60 HZ 1 PH	S1) 3000 VAC @ 3.0 AMP CCS 127
3000/1800 VAC @ 1.0A CCS N PLATE TRANSFORMER WITH HI/LO SEC TAPS		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-1800-3000 VAC @ 1.0A CCS 66
3000/2000 VCT @ 0.35A CCS SPECIAL FOR C&N SERVICES		A-393 C-CORE	10	120 VAC 60 HZ 1 PH	1500-1000-0-1000-1500 VAC @ 0.35A CCS 23
3000/2000 VCT @ 0.5A CCS SPECIAL FOR C&N SERVICES		A-274 C-CORE	10	120 VAC 60 HZ 1 PH	1500-1000-0-1000-1500 VAC @ 0.5A CCS 37
3000/2400 VAC @ 1.5A CCS JKL PLATE TRANSFORMER		A-518 C-CORE	10	0-220-230-240 VAC 60 HZ 1 PH	0-2400-3000 VAC @ 1.5A CCS 66
3000/2500/2000 VAC @ 1A CCS PLATE TRANSFORMER		A-0518/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-2000-2500-3000 VAC @ 1.0 AMP CCS 66
3000/2800/2600V @ 1.5A CS JL PLATE TRANSFORMER		A-518 C-CORE	10	0-220-240 VAC 60 HZ 1 PH	0-2600-2800-3000 VAC @ 1.5A CCS 66
3100/2700/2300V @ 1.5A CCS PLATE TRANSFORMER	PWDP13104	A-518 C-CORE	10	0-220-230-240 VAC 60 HZ 1 PH	0-2300-2700-3100 VAC @ 1.5A CCS 66
32/28/24 VAC @ 15A CCS PROP PITCH PWR XFMR WITH 220 VAC 50/60HZ		EI-162 X 2.5" 29GM6X	2	220 VAC 50/60 HZ 1 PH	S1) 0-24-28-32 VAC @ 15A CCS 18
3200 VAC @ 1.0A CCS SP PLATE XFMR FOR 4000 VDC @ 0.8A FWB CAP-I		A-0518/ C-CORE	10	0-100-110-120 VAC 60 HZ 1 PH	S1) 3200 VAC @ 1.0A CCS 66
3200 VAC @ 1.5A CCS JK PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-230 VAC 60 HZ 1 PH	S1) 3200 VAC @ 1.5A CCS 66
3200 VCT @ .4A & 5 VCT @ 15A PLATE & FIL XFMR FOR SINGLE 3-500Z		EI-162 X 3	4	117 VAC 60 HZ 1 PH	S1) 3200 VCT @ 0.4A ICAS S2) 5.0 VCT @ 15A CCS 21
3200/2800/2400 VAC @ 1.3A CS CCS PLATE XFMR WITH SCREW LUGS ON COIL		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-2400-2800-3200 VAC @ 1.3A CCS 66

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
3300/2300 VAC @ 2.0A CCS KL PLATE TRANSFORMER	PWDP13035	A-0525/ C-CORE	10	0-230-240 VAC 60 HZ 1 PH	S1) 0-2300-3300 VAC @ 2.0A CCS	86
3450 VAC @ 2.5A CCS N PLATE TRANSFORMER		A-0530/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 3450 VAC @ 2.5A CCS	127
3500 VAC @ 1.0A CCS PLATE TRANSFORMER		A-518 C-CORE	10	220 VAC 60 HZ 1PH	S1) 3500 VAC @ 1.0A CCS	66
3500 VAC @ 1.0A ICAS G ADVERTISED UNIT		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 3500 VAC @ 1.0A ICAS	46
3500 VAC @ 1.5A CCS JK PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-230 VAC 60 HZ 1 PH	S1) 3500 VAC @ 1.5A CCS	66
3500 VAC @ 1.5A ICAS N PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 3500 VAC @ 1.5A ICAS	66
3500 VAC @ 2.0A CCS N PLATE TRANSFORMER		A-0555/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 3500 VAC @ 2.0A CCS	119
3500/2000 VAC @ 1.5A CCS JK PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-230 VAC 60 HZ 1 PH	S1) 0-2000-3500 VAC @ 1.5A CCS	66
3500/2400 VAC @ 2.0A CCS L PLATE TRANSFORMER		A-0555/ C-CORE	10	240 VAC 60 HZ 1 PH	0-2400-3500 VAC @ 2.0A CCS	119
3500/3200/3000 VAC @ 1A ICAS PLATE TRANSFORMER		A-0480/ C-CORE	10	0-230-240 VAC 60 HZ 1 PH	0-3000-3200-3500 VAC @ 1.0A ICAS	46
3600 VAC @ 1.0 AMP CCS G WITH TAPS AT 1900-2000-2600 VAC		A-0518/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 0-1900-2000-2600-3600 VAC @ 1.0 AMP CCS	66
3600 VAC @ 1.5A ICAS N PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 3600 VAC @ 1.5A ICAS	66
3600 VAC @ 2.0A ICAS J PLATE TRANSFORMER		A-0525/ C-CORE	10	220 VAC 60 HZ 1 PH	S1) 3600 VAC @ 2.0A ICAS	86
3750 VAC @ 1.0A CCS G		A-518 C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 3750 VAC @ 1.0A CCS	66
3800/3500/2800V @ 1.0A CCS N PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-2800-3500-3800 VAC @ 1.0A CCS	66
3904 VAC @ 1.6A CCS PLATE TRANSFORMER	PWDP13196	EI	4	0-240 VAC 60 HZ 1 PH	S1) 0-3904 VAC @ 1.6A CCS	128
3904 VAC @ 1.6A CCS PLATE TRANSFORMER	PWDP13214	A-0525/ C-CORE	10	0-240 VAC 60 HZ 1 PH	S1) 0-3904 VAC @ 1.6A CCS	86
4000 VAC @ 1.0A CCS N PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 4000 VAC @ 1.0A CCS	66
4000 VAC @ 500 MA CCS		A-0480/ C-CORE	10	230 VAC 50/60 HZ 1 PH	S1) 4000 VAC @ 500 MA CCS	46
4000 VCT @ 1.0A CCS N PLATE TRANSFORMER		A-0518/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 4000 VCT @ 1.0A CCS	66
4000/3200 VAC @ 2.0A CCS N PLATE TRANSFORMER		A-0530/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-3200-4000 VAC @ 2.0A CCS	127
4000/3500/3000 VAC @ 1.5A CS PLATE TRANSFORMER		A-555/C C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-3000-3500-4000 VAC @ 1.5A CCS	119
4000/3500/3000/2500V @ 3A CS		A-540 C-CORE	10	0-230-240 VAC 60 HZ 1 PH	S1) 0-2500-3000-3500-4000 VAC @ 3.0A CCS	164
4200 VAC @ 1.5A CCS KL PLATE TRANSFORMER		A-0530/ C-CORE	10	0-230-240 VAC 60 HZ 1 PH	S1) 4200 VAC @ 1.5A CCS	127
4200 VAC @ 2.0A ICAS F PLATE TRANSFORMER		A-0525/ C-CORE	10	110/220 VAC 60 HZ 1 PH	S1) 4200 VAC @ 2.0A ICAS	86
4200 VCT @ 0.6A CCS I PLATE TRANSFORMER		A-0480/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 4200 VCT @ 0.6A CCS	46
4200/4000/3500/3000 VDC@1.5A CCS,USE WITH 9 HY 1.5A DC CHOKE & 0.2MFD		A-0530/ C-CORE	10	0-220-240 VAC 60HZ 1 PH	S1) 0-3100-3600-4100-4300 VAC @ 1.5A CCS	127
4500 VAC @ 1.5A CCS PLATE TRANSFORMER		A-530 C-CORE	10	0-210-230-240 VAC 60 HZ 1 PH	S1) 4500 VAC @ 1.5A CCS	127

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
4500 VAC @ 2.0A CCS N PLATE TRANSFORMER	A-530/ C-	CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 4500 VAC @ 2.0A CCS	127
4500/3000 VAC @ 2.0A CCS PLATE XFMR WITH 4000 & 3500 VAC TAPS	A-0530/ C-	CORE	10	"=+10,0,-10,208,240 VAC 60 HZ 1 Ph"		127
4500/4000/2600V @ 2.0A CCS N PLATE TRANSFORMER	A-0530/ C-	CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-2600-4000-4500 VAC @ 2.0A CCS	127
4600/4000 VAC @ 1.5A ICAS K PLATE TRANSFORMER	A-0518/ C-	CORE	10	230 VAC 60 HZ 1 PH	S1) 0-4000-4600 VAC @ 1.5A ICAS	66
4600/4000 VAC @ 2.0A CCS N PLATE TRANSFORMER	A-0530/ C-	CORE	10	0-220-240 VAC 60 HZ 1 PH	0-4000-4600 VAC @ 2.0A CCS	127
4800 VAC @ 2.0A CCS N PLATE TRANSFORMER	A-0530/ C-	CORE	10	0-220-240 VAC 60 HZ 1 PH	4800 VAC @ 2.0A CCS	127
4800/4000/3500/2500V @ 3A CS PLATE TRANSFORMER	A-0540/ C-	CORE	10	0-220-240 VAC 60 HZ 1 PH	0-2500-3500-4000-4800 VAC @ 3.0A CCS	164
5.0 VAC @ 10.5 AMP 50 HZ J 220 VAC 50 HZ PRIMARY (SINGLE 8877)	EI-125 SQ	STACK	4	0-220-240 VAC 60 HZ 1 PH	0-4000-4600 VAC @ 2.0A CCS	127
5.0 VCT @ 10.5 AMP CCS D 120 VAC 60 HZ PRIMARY (SINGLE 8877)	I-125 X 1.25		2	120 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 10.5 AMPS CCS	4
5.0 VCT @ 15A CCS F FILAMENT TRANSFORMER (3-500Z OR 4-400A)	EI-137 X 1.375		4	110/220 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 15A CCS	6
5.0 VCT @ 20A CCS JKL RECT FIL XFMR (10 KVDC)	EI-175 X 1.75		2	0-220-230-240 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 20A CCS (10 KVDC INSULATION)	12
5.0 VCT @ 20A CCS L 10 KVDC INSULATION	EI-150 X 1.75		2	240 VAC 60 HZ 1 PH	5.0 VCT @ 20A CCS (10 KVDC INSULATION)	9
5.0 VCT @ 30A & 12 VAC @ 2A	EI-150 X 2		4	120/240 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 30A CCS S2) 12.0 VAC @ 2A CCS	4
5.0 VCT @ 30A G ADVERTISED UNIT (FIL XFMR PAIR 3-500Z'S)	EI-150 X 1.5		4	115/230 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 30A CCS	8
5.0 VCT @ 30A W/BIAS G FIL XFMR FOR PR 3-500Z'S, WITH 90V BIAS	EI-150 X 1.5		4	115/230 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 30A CCS S2) 90 VAC @ 0.2A CCS	8
5.0 VCT @ 4A 10 KVDC FIL RECT FIL XFMR FOR 2 EA 816'S IN SERIES	EI-087 X .875		1	115 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 4A CCS (10 KVDC TEST)	2
5.0 VCT @ 60A CCS SP SPECIAL +5,0,-5,110,125 VAC TAPPED PRI	EI-175 X 2		4	PR) +5,0,-5,110,125 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 60A CCS	14
5.0 VCT @ 60A W/B&F H 90 VAC @ 0.2A BIAS & 12.6 VAC @ 1A LV	EI-175 X 2		5	117/234 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 60A CCS S2) 90 VAC @ 0.2A CCS S3) 12.6 VAC @ 1A CCS	14
5.0 VCT @ 90A CCS LO PROFILE FITS UNDER 4" CHASSIS, SPCL TERRY GAISER	EI-150 X 5"	29GAM6X	4	0-220-230-240-250 VAC 60 HZ 1 PH	S1) 5.0 VCT @ 90A CCS	23
5.0 VCT @ 90A W/BIAS G FILAMENT TRANSFORMER FOR 6 EA 3-500Z'S	EI-175 X 3		4	115/230 VAC 60 Hz	S1) 5.0 VCT @ 90A CCS S2) 90 VAC @ 200 MA	19
5.5 VCT @ 17.5A STP FIL XFMR WITH SPECIAL TAPPED PRIMARY	EI-150 X 1.5		4	0-110-115-120-125 VAC 60 HZ 1 PH	S1) 5.5 VCT @ 17.5A CCS	8
5000 VAC @ 1.5A CCS J PLATE TRANSFORMER	A-0530/ C-	CORE	10	220 VAC 60 HZ 1 PH	S1) 5000 VAC @ 1.5A CCS	127
5000 VCT @ 1.5A CCS PLATE TRANSFORMER	A-555 C-	CORE	10	117/234 VAC 60 HZ 1PH	S1) 5000 VCT @ 1.5A CCS	119
5000 VCT @ 2.0A CCS J PLATE TRANSFORMER (WITH CENTER TAP)	A-530 C-	CORE	10	220 VAC 60 HZ 1PH	S1) 5000 VCT @ 2.0A CCS	127
5000 VCT @ 500MA CCS I GENERAL PURPOSE PLATE XFMR FOR FWCT	A-480 C-	CORE	10	120/240 VAC 60 HZ	S1) 5000 VCT @ 500MA CCS	46
5000/4300/3600/3000V @ 2A CS PLATE TRANSFORMER	A-0530/ C-	CORE	10	0-210-225-240 VAC 60 HZ 1PH	S1) 0-3000-3600-4300-5000 VAC @ 2.0A CCS	127
5000/4500 VAC @ 1.5A ICAS K 4500 VDC OR 4000 VDC @ 1.5A ICAS	A-525/C C-	CORE	10	230 VAC 60 HZ 1 PH	0-4500-5000 VAC @ 1.5A ICAS	86
5000/4500/4000 VAC @ 2A CS N PLATE TRANSFORMER WITH 220/240 VAC PRI	A-0530/ C-	CORE	10	0-220-240 VAC 60 HZ 1PH	S1) 0-4000-4500-5000 VAC @ 2.0A CCS	127

Description	Hammond Part Number	Core	Style (see above)	Primary	Secondary	Approx. Weight (lbs)
5000/4700/4400/4000V @ 2A CS PLATE TRANSFORMER		A-0530/ C-CORE	10	0-220-230-240 VAC 60 HZ 1PH	0-4000-4400-4700-5000 VAC @ 2.0A CCS	127
5200/4400 VAC @ 1.5A CCS V WITH SEC TAPS @ 5000 & 4700 VAC		A-0530/ C-CORE	10	PR) +10,0,-10,210,240 VAC 60 HZ 1 PH	S1) 0-4400-4700-5000-5200 VAC @ 1.5A CCS	127
550 VCT @ 0.3A CCS D POWER TRANSFORMER		EI-150 X 1.5	2	120 VAC 60 HZ 1 PH	S1) 550 VCT @ 0.3A CCS	8
5600 VCT @ 1.5A CCS SP FWCT PLATE TRANSFORMER		A-0525/ C-CORE	10	0-220-240-260 VAC 60 HZ 1 PH	S1) 2800-0-2800 VAC @ 1.5A CCS	86
5800 VCT @ 1.0A CCS FWCT G 2.9 KVA FWCT PLATE TRANSFORMER		A-518 C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 5800 VCT @ 1.0A CCS FWCT	66
6.3 VCT @ 10A CCS G FILAMENT TRANSFORMER		EI-137 X 1.375	4	115/230 VAC 60 HZ 1 PH	S1) 6.3 VCT @ 10A CCS	6
6.3 VCT @ 100A D FILAMENT TRANSFORMER		EI-162 X 3.5	2	120 VAC 60 HZ 1PH	S1) 6.3 VCT @ 100A CCS	24
6.3 VCT @ 16A & 24 VCT @ 3A FILAMENT & CONTROL TRANSFORMER		EI-150 X 2	5	115/230 VAC 60 HZ 1 PH	S1) 6.3 VCT @ 16A CCS S2) 24 VCT @ 3A CCS	10
6.3 VCT @ 160A CCS N 3CX15000A7 FILAMENT TRANSFORMER	PWDF13127	A-0393/ C-CORE	10	0-220-240 VAC 60 HZ 1PH	6.3 VCT @ 160A CCS	23
6.3 VCT @ 20A D FILAMENT TRANSFORMER -- ADVERTISED UNIT		EI-150 X 1.5	2	120 VAC 60 HZ 1 PH	6.3 VCT @ 20A CCS	8
6.3 VCT @ 30A CCS (G) FILAMENT TRANSFORMER		EI-150 X 2	4	115/230 VAC 60 HZ 1 PH	S1) 6.3 VCT @ 30A CCS	10
6.3 VCT @ 50A CCS JKL STYLE #5 WITH POTTED END BELLS		EI-175 X 2" 29GAM6X	5	0-220-230-240 VAC 60 HZ 1 PH	S1) 6.3 VCT @ 50A CCS	14
6000 VCT @ 0.8A CCS G PLATE TRANSFORMER FOR FWCT RECTIFIER		A-0480/ C-CORE	10	115/230 VAC 60 HZ 1 PH	S1) 6000 VCT @ 0.8A CCS (FWCT RECTIFIER)	46
6000/3000 VAC @ 1.0A CCS KCB 230 VAC PRI CB TAPS FOR 6,5,4,3 KVAC		A-0530/ C-CORE	10	0-230-276-345-460 VAC 60 HZ 1 PH	S1) 6000 VAC @ 1.0A CCS	127
6000/5000/4000/3000V @ 0.9A CCS PLATE TRANSFORMER		A-0525/ C-CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 0-3000-4000-5000-6000 VAC @ 0.9A CCS	86
7.0 VCT @ 160A CCS I DUAL 3CX6000A7/YU-148 FILAMENT XFMR		A-0274/ C-CORE	10	120/240 VAC 60 HZ 1 PH	S1) 7.0 VCT @ 160A CCS	37
7.0 VCT @ 85A N YU-148 FILAMENT TRANSFORMER	PWDF13050	EI-162 X 3	2	0-220-240 VAC 60 HZ 1 PH	S1) 7.0 VCT @ 85A CCS	21
7.5 VCT @ 100A CCS D FILAMENT TRANSFORMER		EI-162 X 3.5	2	120 VAC 60 HZ 1PH	S1) 7.5 VCT @ 100A CCS	24
7.5 VCT @ 100A G FILAMENT TRANSFORMER	PWDF13185	EI-162 X 3.5	2	115/230 VAC 50/60 HZ 1PH	S1) 7.5 VCT @ 100A CCS	24
7.5 VCT @ 21A ABD 4-1000A OR 3-1000Z FILAMENT TRANSFORMER		EI-150 X 2	5	0-110-115-120 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 21A CCS	10
7.5 VCT @ 21A E 4-1000A OR 3-1000Z FILAMENT TRANSFORMER		EI-150 X 2	5	0-105-117 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 21A CCS	10
7.5 VCT @ 21A LO PROFILE FILAMENT TRANSFORMER		EI-125 X 2	4	0-105-117 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 21A CCS	7
7.5 VCT @ 24A & 5.0 VCT @ 8A FIL XFMR FOR 2 EA #450TL & 1 EA #254		EI-175 X 2	4	0-220-230-240 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 24A CCS S2) 5.0 VCT @ 8A CCS	14
7.5 VCT @ 42A CCS LP SP LO PROFILE SPECIAL PRIMARY FOR T. GAISER		EI-150 X 2.5" 29GAM6	2	0-115-125 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 42A CCS	12
7.5 VCT @ 42A CCS SP FILAMENT TRANSFORMER WITH SPECIAL PRI		EI-175 X 2" 29GAM6X	5	0-228-230-232 50 HZ 1 PH	S1) 7.5 VCT @ 42A CCS	14
7.5 VCT @ 55A G ADVERTISED UNIT	PWDF13081	EI-162 X 2	2	115/230 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 55A CCS	15
7.5 VCT @ 75A G ADVERTISED UNIT		EI-162 X 3	2	115/230 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 75A CCS	21
7.5 VCT @ 75A N 220/240 VAC TAPPED PRIMARY		EI-162 X 3	2	0-220-240 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 75A CCS	21
7.5 VCT @ 110A CCS FILAMENT TRANSFORMER 120/240 VAC DUAL PRIMARY	PWDF13038	EI-162 X 3.5	2	120/240 VAC 60 HZ 1 PH	S1) 7.5 VCT @ 110A CCS	24

Description	Hammond Part Number	Core	Style (see above)	Approx. Weight (lbs)	
				Primary	Secondary
7.5/6.3 VCT @ 160A CCS D DUAL VOLTAGE FIL XFMR WITH 120V PRI TAPS	A-0274/ C-	CORE	10	0-120-143 VAC 60 HZ 1 PH	7.5/6.3 VCT @ 160A CCS 37
7.5/6.3 VCT @ 160A CCS L DUAL VOLTAGE FIL XFMR WITH 240V PRI TAPS	A-0274/ C-	CORE	10	0-240-286 VAC 60 HZ 1 PH	7.5/6.3 VCT @ 160A CCS 37
7.5/6.3 VCT @ 26A & 26V @ 1A SPECIAL 3CX1200 & YU-121 FIL XFMR	EI-175 X 1.75		4	PR) +45,0,220,228,236,244 VAC 60 HZ 1 PH	S1) 7.5/6.3 VCT @ 26A CCS S2) 26 VAC @ 1A CCS
7000 VCT @ 0.9A CCS N 4900 VDC @ 0.9A FWCT 4-1000A PLATE XFMR	A-0525/ C-	CORE	10	0-220-240 VAC 60 HZ 1 PH	S1) 7000 VCT @ 0.9A CCS (FWCT)
7200 VCT @ 2.1 AMP CCS FOR FWCT TO DELIVER 4400 VDC @ 1.5A CCS	A-555 C-	CORE	10	0-220 VAC 60 HZ	S1) 0-3600-7200 VCT @ 2.1A CCS
850 VAC @ 1.0A CCS D 120 VAC PRIMARY & WIRE LEADS	A-0393/ C-	CORE	10	PR) 120 VAC 60 HZ 1 PH	S1) 850 VAC @ 1.0A CCS

Data subject to change without notice

© 2022. Hammond Manufacturing Ltd. All rights reserved.

